SIEMENS

Data sheet

3RT2317-2AF00



Contactor, AC-1, 22 A/400 V/40 $^\circ\text{C},$ S00, 4-pole, 110 V AC, 50/60 Hz, Spring-type terminal

product brand name	SIRIUS
product designation	Contactor
product type designation	3RT23
General technical data	
size of contactor	S00
product extension	
 function module for communication 	No
auxiliary switch	Yes
power loss [W] for rated value of the current	
 at AC in hot operating state 	6.4 W
 at AC in hot operating state per pole 	1.6 W
insulation voltage	
 of main circuit with degree of pollution 3 rated value 	690 V
 of the auxiliary and control circuit with degree of pollution 3 rated value 	690 V
surge voltage resistance	
 of main circuit rated value 	6 kV
 of auxiliary circuit rated value 	6 kV
shock resistance at rectangular impulse	
● at AC	7,3g / 5 ms, 4,7g / 10 ms
shock resistance with sine pulse	
• at AC	11,4g / 5 ms, 7,3g / 10 ms
mechanical service life (switching cycles)	
 of contactor typical 	30 000 000
 of the contactor with added auxiliary switch block typical 	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	10/01/2009
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
 during operation 	-25 +60 °C
during storage	-55 +80 °C
relative humidity minimum	10 %
relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %
Main circuit	
number of poles for main current circuit	4
number of NO contacts for main contacts	4
operational current	

• at AC-1 at 400 V at ambient temperature 40 °C rated value	22 A		
 at AC-1 — up to 690 V at ambient temperature 40 °C 	22 A		
rated value — up to 690 V at ambient temperature 60 °C rated value	20 A		
• at AC-3			
— at 400 V rated value	12 A		
 at AC-4 at 400 V rated value 	8.5 A		
minimum cross-section in main circuit at maximum AC-1 rated value	4 mm ²		
operating power			
 at AC-3 at 400 V rated value 	5.5 kW		
 at AC-4 at 400 V rated value 	4 kW		
short-time withstand current in cold operating state up to 40 °C			
 limited to 1 s switching at zero current maximum 	Use minimum cross-section acc. to AC-1 rated value		
 limited to 5 s switching at zero current maximum 	Use minimum cross-section acc. to AC-1 rated value		
 limited to 10 s switching at zero current maximum 	Use minimum cross-section acc. to AC-1 rated value		
 limited to 30 s switching at zero current maximum 	Use minimum cross-section acc. to AC-1 rated value		
 limited to 60 s switching at zero current maximum 	Use minimum cross-section acc. to AC-1 rated value		
no-load switching frequency			
• at AC	10 000 1/h		
operating frequency at AC-1 maximum	1 000 1/h		
Control circuit/ Control			
type of voltage	AC		
type of voltage of the control supply voltage	AC		
control supply voltage at AC			
• at 50 Hz rated value	110 V		
at 60 Hz rated value	110 V		
operating range factor control supply voltage rated			
value of magnet coil at AC			
• at 50 Hz	0.8 1.1		
	0.85 1.1		
● at 60 Hz	0.00 1.1		
at 60 Hz apparent pick-up power of magnet coil at AC	0.00 1.1		
	37 VA		
apparent pick-up power of magnet coil at AC			
apparent pick-up power of magnet coil at AC • at 50 Hz	37 VA		
 apparent pick-up power of magnet coil at AC at 50 Hz at 60 Hz 	37 VA		
 apparent pick-up power of magnet coil at AC at 50 Hz at 60 Hz inductive power factor with closing power of the coil 	37 VA 33 VA		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz	37 VA 33 VA 0.8		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz	37 VA 33 VA 0.8		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC	37 VA 33 VA 0.8 0.75		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz	37 VA 33 VA 0.8 0.75 5.7 VA		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz • at 60 Hz • at 60 Hz • at 60 Hz	37 VA 33 VA 0.8 0.75 5.7 VA		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz • at 60 Hz • at 60 Hz • at 60 Hz	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz • at 60 Hz • at 50 Hz • at 60 Hz • at 50 Hz	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz • at 60 Hz • at 60 Hz	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz • at AC • at AC	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25 9 35 ms		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz • at	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25 9 35 ms 7 13 ms		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 60 Hz • at AC opening delay • at AC arcing time	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25 9 35 ms 7 13 ms 10 15 ms		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz closing delay • at AC opening delay • at AC arcing time control version of the switch operating mechanism Auxiliary circuit	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25 9 35 ms 7 13 ms 10 15 ms		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 60 Hz closing delay • at AC opening delay • at AC arcing time control version of the switch operating mechanism	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25 9 35 ms 7 13 ms 10 15 ms		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 60 Hz closing delay • at AC opening delay • at AC arcing time control version of the switch operating mechanism Auxiliary circuit number of NC contacts for auxiliary contacts • attachable	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25 9 35 ms 7 13 ms 10 15 ms Standard A1 - A2		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 60 Hz closing delay • at AC opening delay • at AC arcing time control version of the switch operating mechanism Auxiliary circuit number of NC contacts for auxiliary contacts • attachable number of NO contacts for auxiliary contacts	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25 9 35 ms 7 13 ms 10 15 ms Standard A1 - A2 2		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 60 Hz closing delay • at AC opening delay • at AC arcing time control version of the switch operating mechanism Auxiliary circuit number of NC contacts for auxiliary contacts • attachable number of NO contacts for auxiliary contacts • attachable	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25 9 35 ms 7 13 ms 10 15 ms Standard A1 - A2		
apparent pick-up power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with closing power of the coil • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz apparent holding power of magnet coil at AC • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 50 Hz • at 60 Hz inductive power factor with the holding power of the coil • at 60 Hz closing delay • at AC opening delay • at AC arcing time control version of the switch operating mechanism Auxiliary circuit number of NC contacts for auxiliary contacts • attachable number of NO contacts for auxiliary contacts	37 VA 33 VA 0.8 0.75 5.7 VA 4.4 VA 0.25 0.25 9 35 ms 7 13 ms 10 15 ms Standard A1 - A2 2		

design of the fuse link				
design of the fuse link				
 for short-circuit protection of the main circuit with type of coordination 1 required 				
— with type of coordination 1 required	gG: 35 A (690 V, 100 kA)			
— with type of assignment 2 required	gG: 20 A (690 V, 100 kA)			
 for short-circuit protection of the auxiliary switch required 	gG: 10 A (690 V, 1 kA)			
Installation/ mounting/ dimensions				
mounting position	+/-180° rotation possible on vertical mounting surface; can be tilted			
	forward and backward by +/- 22.5° on vertical mounting surface			
fastening method	screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 60715			
side-by-side mounting	Yes			
height	70 mm			
width	45 mm			
depth	73 mm			
required spacing				
with side-by-side mounting				
— forwards	10 mm			
— upwards	10 mm			
— downwards	10 mm			
— at the side	0 mm			
 for grounded parts 				
— forwards	10 mm			
— upwards	10 mm			
— at the side	6 mm			
— downwards	10 mm			
 for live parts 				
— forwards	10 mm			
— upwards	10 mm			
— downwards	10 mm			
— at the side	6 mm			
Connections/ Terminals				
type of electrical connection				
 for main current circuit 	spring-loaded terminals			
 for auxiliary and control circuit 	spring-loaded terminals			
 at contactor for auxiliary contacts 	Spring-type terminals			
 of magnet coil 	Spring-type terminals			
type of connectable conductor cross-sections				
 for main contacts 				
— solid	2x (0.5 4 mm²)			
— solid or stranded	2x (0,5 4 mm²)			
 finely stranded with core end processing 	2x (0.5 2.5 mm²)			
 finely stranded without core end processing 	2x (0.5 2.5 mm²)			
 at AWG cables for main contacts 	2x (20 12)			
connectable conductor cross-section for main contacts				
• solid	0.5 4 mm ²			
 solid or stranded 	0.5 4 mm²			
• stranded	0.5 4 mm²			
 finely stranded with core end processing 	0.5 2.5 mm ²			
 finely stranded without core end processing 				
	0.5 2.5 mm²			
connectable conductor cross-section for auxiliary contacts	0.5 2.5 mm²			
• solid or stranded	0.5 2.5 mm² 0.5 4 mm²			
contacts	0.5 2.5 mm²			
 contacts solid or stranded finely stranded with core end processing finely stranded without core end processing 	0.5 2.5 mm² 0.5 4 mm²			
contactssolid or strandedfinely stranded with core end processing	0.5 2.5 mm ² 0.5 4 mm ² 0.5 2.5 mm ²			
 contacts solid or stranded finely stranded with core end processing finely stranded without core end processing 	0.5 2.5 mm ² 0.5 4 mm ² 0.5 2.5 mm ²			
contacts solid or stranded finely stranded with core end processing finely stranded without core end processing type of connectable conductor cross-sections	0.5 2.5 mm ² 0.5 4 mm ² 0.5 2.5 mm ²			
contacts • solid or stranded • finely stranded with core end processing • finely stranded without core end processing type of connectable conductor cross-sections • for auxiliary contacts	0.5 2.5 mm ² 0.5 4 mm ² 0.5 2.5 mm ² 0.5 2.5 mm ²			

-	ided without core end p for auxiliary contacts	rocessing	2x (0.5 2.5 mm²) 2x (20 12)			
	led connectable cond	uctor cross	2x (20 12)			
section						
 for main contacts 			20 12			
 for auxiliary contacts 			20 12			
Safety related data						
product function						
	mirror contact according to IEC 60947-4-1		Yes; with 3RH29			
T1 value for proof test interval or service life according to		according to	20 y			
IEC 61508 protection class IP on the front according to IEC 60529		to IEC	IP20			
touch protection on	the front according to	IEC 60529	finger-safe, for vertical contact from the front			
Communication/ Prote	-		-			
product function bus	s communication		No			
Certificates/ approval						
General Product Ap					EMC	
General Product Ap	provar				LING	
SP CM		<u>Confirmation</u>		EHC	RCM	
Functional Safety/Safety of Machinery	Declaration of Conf	ormity	Test Certifica	tes	Marine / Shipping	
<u>Type Examination</u> <u>Certificate</u>	UK CA	CE EG-Konf.	<u>Type Test Cer</u> <u>ates/Test Re</u> r		ABS	
Marine / Shipping						
BUREAU VERITAS		Llovd's Register urs	PRS	RINA	KMRS RMRS	
other						
Environmental Con- firmations	<u>Confirmation</u>					
Further information						
Information- and Downloadcenter (Catalogs, Brochures,) https://www.siemens.com/ic10 Industry Mall (Online ordering system) https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT2317-2AF00 Cax online generator http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT2317-2AF00 Service&Support (Manuals, Certificates, Characteristics, FAQs,)						

- Service&Support (Manuals, Certificates, Characteristics, FAQs,...)
- https://support.industry.siemens.com/cs/ww/en/ps/3RT2317-2AF00

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RT2317-2AF00&lang=en

Characteristic: Tripping characteristics, I²t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RT2317-2AF00/char

Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT2317-2AF00&objecttype=14&gridview=view1

last modified:

3/18/2022 🖸