# **SIEMENS**

Data sheet 3RT2016-1AN21



Power contactor, AC-3 9 A, 4 kW / 400 V 1 NO, 220 V AC, 50 / 60 Hz 3-pole, Size S00 screw terminal

product brand name	SIRIUS
product designation	Power contactor
product type designation	3RT2
General technical data	
size of contactor	S00
product extension	
<ul> <li>function module for communication</li> </ul>	No
auxiliary switch	Yes
power loss [W] for rated value of the current	
<ul> <li>at AC in hot operating state</li> </ul>	0.9 W
<ul> <li>at AC in hot operating state per pole</li> </ul>	0.3 W
<ul> <li>without load current share typical</li> </ul>	4.2 W
insulation voltage	
<ul> <li>of main circuit with degree of pollution 3 rated value</li> </ul>	690 V
<ul> <li>of auxiliary circuit with degree of pollution 3 rated value</li> </ul>	690 V
surge voltage resistance	
<ul> <li>of main circuit rated value</li> </ul>	6 kV
of auxiliary circuit rated value	6 kV
maximum permissible voltage for safe isolation between coil and main contacts according to EN 60947-1	400 V
shock resistance at rectangular impulse	
• at AC	6,7g / 5 ms, 4,2g / 10 ms
shock resistance with sine pulse	
• at AC	10,5g / 5 ms, 6,6g / 10 ms
mechanical service life (switching cycles)	
<ul> <li>of contactor typical</li> </ul>	30 000 000
<ul> <li>of the contactor with added electronically optimized auxiliary switch block typical</li> </ul>	5 000 000
<ul> <li>of the contactor with added auxiliary switch block typical</li> </ul>	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	10/01/2009
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
<ul> <li>during operation</li> </ul>	-25 +60 °C
during storage	-55 +80 °C
relative humidity minimum	10 %
relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %

Main circuit		
number of poles for main current circuit	3	
number of NO contacts for main contacts	3	
operating voltage		
at AC-3 rated value maximum	690 V	
at AC-3e rated value maximum	690 V	
operational current		
at AC-1 at 400 V at ambient temperature 40 °C rated value	22 A	
• at AC-1		
<ul> <li>up to 690 V at ambient temperature 40 °C rated value</li> </ul>	22 A	
— up to 690 V at ambient temperature 60 $^{\circ}\text{C}$ rated value	20 A	
• at AC-3		
— at 400 V rated value	9 A	
— at 500 V rated value	7.7 A	
— at 690 V rated value	6.7 A	
• at AC-3e		
— at 400 V rated value	9 A	
— at 500 V rated value	7.7 A	
— at 690 V rated value	6.7 A	
• at AC-4 at 400 V rated value	8.5 A	
• at AC-5a up to 690 V rated value	19.4 A	
at AC-5b up to 400 V rated value	7.4 A	
• at AC-6a		
up to 230 V for current peak value n=20 rated value	5.3 A	
<ul> <li>up to 400 V for current peak value n=20 rated value</li> </ul>	5.3 A	
<ul> <li>up to 500 V for current peak value n=20 rated value</li> </ul>	5.3 A	
<ul> <li>up to 690 V for current peak value n=20 rated value</li> <li>at AC-6a</li> </ul>	5 A	
— up to 230 V for current peak value n=30 rated value	3.5 A	
<ul> <li>up to 400 V for current peak value n=30 rated value</li> </ul>	3.5 A	
<ul> <li>up to 500 V for current peak value n=30 rated value</li> </ul>	3.6 A	
— up to 690 V for current peak value n=30 rated value	3.3 A	
minimum cross-section in main circuit at maximum AC-1 rated value operational current for approx. 200000 operating	4 mm <sup>2</sup>	
cycles at AC-4		
at 400 V rated value	4.1 A	
at 690 V rated value	3.3 A	
operational current		
• at 1 current path at DC-1		
— at 24 V rated value	20 A	
— at 110 V rated value	2.1 A	
— at 220 V rated value	0.8 A	
— at 440 V rated value	0.6 A	
— at 600 V rated value	0.6 A	
with 2 current paths in series at DC-1	0.07.	
— at 24 V rated value	20 A	
— at 24 V rated value  — at 110 V rated value	12 A	
— at 110 V rated value  — at 220 V rated value	1.6 A	
— at 440 V rated value	0.8 A	
— at 600 V rated value	0.7 A	
<ul> <li>with 3 current paths in series at DC-1</li> </ul>		

— at 24 V rated value	20 A
— at 110 V rated value	20 A
— at 220 V rated value	20 A
— at 440 V rated value	1.3 A
— at 600 V rated value	1 A
<ul><li>at 1 current path at DC-3 at DC-5</li></ul>	
— at 24 V rated value	20 A
— at 110 V rated value	0.1 A
<ul> <li>with 2 current paths in series at DC-3 at DC-5</li> </ul>	
— at 24 V rated value	20 A
— at 110 V rated value	0.35 A
<ul> <li>with 3 current paths in series at DC-3 at DC-5</li> </ul>	
— at 24 V rated value	20 A
— at 110 V rated value	20 A
— at 220 V rated value	1.5 A
— at 440 V rated value	0.2 A
— at 600 V rated value	0.2 A
operating power	
at AC-2 at 400 V rated value	4 kW
• at AC-3	
— at 230 V rated value	2.2 kW
— at 400 V rated value	4 kW
— at 500 V rated value	4 kW
— at 690 V rated value	5.5 kW
• at AC-3e	
— at 230 V rated value	2.2 kW
— at 400 V rated value	4 kW
— at 500 V rated value	4 kW
— at 690 V rated value	5 kW
operating power for approx. 200000 operating cycles	O KW
at AC-4	
at 400 V rated value	2 kW
at 690 V rated value	2.5 kW
operating apparent power at AC-6a	
<ul> <li>up to 230 V for current peak value n=20 rated value</li> </ul>	2 kVA
<ul> <li>up to 400 V for current peak value n=20 rated value</li> </ul>	3.6 kVA
<ul> <li>up to 500 V for current peak value n=20 rated value</li> </ul>	4.6 kVA
<ul> <li>up to 690 V for current peak value n=20 rated value</li> </ul>	5.9 kVA
operating apparent power at AC-6a	
• up to 230 V for current peak value n=30 rated value	1.3 kVA
• up to 400 V for current peak value n=30 rated value	2.4 kVA
• up to 500 V for current peak value n=30 rated value	3.1 kVA
• up to 690 V for current peak value n=30 rated value	4 kVA
short-time withstand current in cold operating state	
up to 40 °C	
<ul> <li>limited to 1 s switching at zero current maximum</li> </ul>	155 A; Use minimum cross-section acc. to AC-1 rated value
<ul> <li>limited to 5 s switching at zero current maximum</li> </ul>	111 A; Use minimum cross-section acc. to AC-1 rated value
<ul> <li>limited to 10 s switching at zero current maximum</li> </ul>	86 A; Use minimum cross-section acc. to AC-1 rated value
<ul> <li>limited to 30 s switching at zero current maximum</li> </ul>	66 A; Use minimum cross-section acc. to AC-1 rated value
<ul> <li>limited to 60 s switching at zero current maximum</li> </ul>	55 A; Use minimum cross-section acc. to AC-1 rated value
no-load switching frequency	
• at AC	10 000 1/h
operating frequency	
• at AC-1 maximum	1 000 1/h
• at AC-2 maximum	750 1/h
• at AC-3 maximum	750 1/h
at AC-3e maximum	750 1/h
• at AC-4 maximum	250 1/h
Control circuit/ Control	
type of voltage of the control supply voltage	AC
type or voltage or the control supply voltage	/ NO

control supply voltage at AC	
at 50 Hz rated value	220 V
at 60 Hz rated value	220 V
operating range factor control supply voltage rated value of magnet coil at AC	
• at 50 Hz	0.8 1.1
• at 60 Hz	0.85 1.1
apparent pick-up power of magnet coil at AC	0.00 1.1
• at 50 Hz	27 VA
• at 60 Hz	24.3 VA
inductive power factor with closing power of the coil	ZT.S VA
• at 50 Hz	0.8
• at 60 Hz	0.75
apparent holding power of magnet coil at AC	0.70
• at 50 Hz	4.2 VA
• at 60 Hz	3.3 VA
inductive power factor with the holding power of the	0.0 V//
coil	
● at 50 Hz	0.25
● at 60 Hz	0.25
closing delay	
• at AC	9 35 ms
opening delay	
at AC	7 13 ms
arcing time	10 15 ms
control version of the switch operating mechanism	Standard A1 - A2
Auxiliary circuit	
number of NO contacts for auxiliary contacts	1
instantaneous contact operational current at AC-12 maximum	10 A
· ·	10 A
Ongrational current at AC-15	
operational current at AC-15	10 Δ
• at 230 V rated value	10 A
<ul><li>at 230 V rated value</li><li>at 400 V rated value</li></ul>	3 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> </ul>	3 A 2 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul>	3 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12	3 A 2 A 1 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> </ul>	3 A 2 A 1 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> </ul>	3 A 2 A 1 A 10 A 6 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> </ul>	3 A 2 A 1 A 10 A 6 A 6 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> </ul>	3 A 2 A 1 A 10 A 6 A 6 A 3 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> </ul>	3 A 2 A 1 A 10 A 6 A 6 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> </ul>	3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> </ul>	3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A 1 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> </ul>	3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A 1 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> </ul> operational current at DC-13	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> </ul> operational current at DC-13 <ul> <li>at 24 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> </ul> operational current at DC-13 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A  10 A 2 A 1 A 0.15 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> </ul> operational current at DC-13 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> </ul> at 60 V rated value <ul> <li>at 60 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A  10 A 2 A 1 A 0.15 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> </ul> operational current at DC-13 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 60 V rated value</li> </ul> at 110 V rated value <ul> <li>at 110 V rated value</li> <li>at 110 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> </ul> operational current at DC-12 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> </ul> operational current at DC-13 <ul> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> </ul> at 1125 V rated value <ul> <li>at 115 V rated value</li> <li>at 125 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> <li>operational current at DC-12</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A 0.3 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> <li>operational current at DC-12</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 126 V rated value</li> <li>at 127 V rated value</li> <li>at 200 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A  10 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A 0.3 A 0.1 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> <li>operational current at DC-12</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A  10 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A 0.3 A 0.1 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> <li>operational current at DC-12</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 126 V rated value</li> <li>at 127 V rated value</li> <li>at 200 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A  10 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A 0.3 A 0.1 A
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> <li>operational current at DC-12</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 480 V rated value</li> <li>at 480 V rated value</li> <li>at 600 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A 0.3 A 0.1 A 1 faulty switching per 100 million (17 V, 1 mA)
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> <li>operational current at DC-12</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A 0.3 A 0.1 A 1 faulty switching per 100 million (17 V, 1 mA)
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> <li>operational current at DC-12</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 480 V rated value</li> <li>at 480 V rated value</li> <li>at 600 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A 0.3 A 0.1 A 1 faulty switching per 100 million (17 V, 1 mA)
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> <li>operational current at DC-12</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 60 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 48 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 600 V rated value</li> <li>at 480 V rated value</li> <li>at 480 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A 0.3 A 0.1 A 1 faulty switching per 100 million (17 V, 1 mA)
<ul> <li>at 230 V rated value</li> <li>at 400 V rated value</li> <li>at 500 V rated value</li> <li>at 690 V rated value</li> <li>operational current at DC-12</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 600 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 24 V rated value</li> <li>at 48 V rated value</li> <li>at 110 V rated value</li> <li>at 110 V rated value</li> <li>at 125 V rated value</li> <li>at 125 V rated value</li> <li>at 220 V rated value</li> <li>at 600 V rated value</li> <li>at 480 V rated value</li> <li>at 600 V rated value</li> </ul>	3 A 2 A 1 A  10 A 6 A 6 A 3 A 2 A 1 A 0.15 A  10 A 2 A 2 A 1 A 0.9 A 0.3 A 0.1 A 1 faulty switching per 100 million (17 V, 1 mA)  7.6 A 9 A

— at 200/208 V rated value	2 hp
<ul> <li>at 220/230 V rated value</li> </ul>	3 hp
— at 460/480 V rated value	5 hp
— at 575/600 V rated value	7.5 hp
contact rating of auxiliary contacts according to UL	A600 / Q600
Short-circuit protection	
design of the fuse link	
<ul> <li>for short-circuit protection of the main circuit</li> <li>— with type of coordination 1 required</li> </ul>	gG: 35A (690V,100kA), aM: 20A (690V,100kA), BS88: 35A (415V,80kA)
with type of assignment 2 required	gG: 20A (690V,100kA), aM: 16A (690V, 100kA), BS88: 20A (415V, 80kA)
<ul> <li>for short-circuit protection of the auxiliary switch required</li> </ul>	gG: 10 A (500 V, 1 kA)
Installation/ mounting/ dimensions	
mounting position	+/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface
fastening method	screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 60715
• side-by-side mounting	Yes
height	58 mm
width	45 mm
depth	73 mm
required spacing	
<ul><li>with side-by-side mounting</li></ul>	
— forwards	10 mm
— upwards	10 mm
— downwards	10 mm
— at the side	0 mm
for grounded parts	
— forwards	10 mm
— upwards	10 mm
— at the side	6 mm
— downwards	10 mm
• for live parts	40
— forwards	10 mm
— upwards — downwards	10 mm 10 mm
— at the side	6 mm
Connections/ Terminals	Ollilli
type of electrical connection  • for main current circuit	screw-tyne terminals
for main current circuit     for auxiliary and control circuit	screw-type terminals screw-type terminals
at contactor for auxiliary contacts	Screw-type terminals Screw-type terminals
of magnet coil	Screw-type terminals Screw-type terminals
type of connectable conductor cross-sections	Section type terminals
• for main contacts	
— solid	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²), 2x 4 mm²
solid or stranded	2x (0,5 1,5 mm²), 2x (0,75 2,5 mm²), 2x 4 mm²
finely stranded with core end processing	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
at AWG cables for main contacts	2x (20 16), 2x (18 14), 2x 12
connectable conductor cross-section for main	
contacts	0.5 4 mm²
• solid	0.5 4 mm² 0.5 4 mm²
stranded     finely stranded with core end processing	0.5 4 mm² 0.5 2.5 mm²
• finely stranded with core end processing	0.5 2.3 IIIIII
connectable conductor cross-section for auxiliary contacts	
solid or stranded	0.5 4 mm²
finely stranded with core end processing	0.5 2.5 mm²
type of connectable conductor cross-sections	
for auxiliary contacts	

<ul><li>— solid or stranded</li></ul>	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²), 2x 4 mm²
<ul> <li>finely stranded with core end processing</li> </ul>	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
<ul> <li>at AWG cables for auxiliary contacts</li> </ul>	2x (20 16), 2x (18 14), 2x 12
AWG number as coded connectable conductor cross section	
<ul> <li>for main contacts</li> </ul>	20 12
<ul> <li>for auxiliary contacts</li> </ul>	20 12
Safety related data	
product function	
<ul> <li>mirror contact according to IEC 60947-4-1</li> </ul>	Yes; with 3RH29
B10 value with high demand rate according to SN 31920	1 000 000
proportion of dangerous failures	
<ul> <li>with low demand rate according to SN 31920</li> </ul>	40 %
<ul> <li>with high demand rate according to SN 31920</li> </ul>	73 %
failure rate [FIT] with low demand rate according to SN 31920	100 FIT
T1 value for proof test interval or service life according to IEC 61508	20 y
protection class IP on the front according to IEC 60529	IP20
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front
suitability for use	
<ul> <li>safety-related switching OFF</li> </ul>	Yes

# Certificates/ approvals

### **General Product Approval**





Confirmation



<u>KC</u>



Functional
EMC Safety/Safety of Machinery Declaration of Conformity Test Certificates



Type Examination Certificate





Type Test Certificates/Test Report

Special Test Certificate

## Marine / Shipping













Marine / Shipping

other



Confirmation



Confirmation

#### Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT2016-1AN21

#### Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT2016-1AN21

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RT2016-1AN21

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) <a href="http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RT2016-1AN21&lang=en">http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RT2016-1AN21&lang=en</a>

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RT2016-1AN21/char

Further characteristics (e.g. electrical endurance, switching frequency)
<a href="http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT2016-1AN21&objecttype=14&gridview=view1">http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT2016-1AN21&objecttype=14&gridview=view1</a>

6/2/2022 last modified: