

# User Manual

# **BG-CAP-HA** HDMI to USB Video Capture Device



**All Rights Reserved** 

#### Introduction

The BG-CAP-HA is a HDMI to USB video capture device. The product is designed to capture video and audio signal from the HDMI source. The content captured can be saved to the PC/Laptop through a USB cable.

#### Features

- Capture video and audio from HDMI sources.
- HDMI video resolution is up to 4K@60Hz 4:4:4, HDR10
- Supports HDMI loop output for display device connection.
- Capture resolutions up to 1080p at 60 frames per second through USB port.
- Compatible with multiple third-party applications, such as OBS/ VLC/PotPlayer/ YouTube on Windows, QuickTime on Mac OS X.
- Supports embedding audio (audio input) and de-embedding audio (audio output).
- Powered from USB port, no external power supply required.

#### Package List

Please make sure all the items listed below are in the package. If anything is missing or damaged, please contact your distributor for a replacement.

- 1x BG-CAP-HA
- 1x USB Cable
- 1x User Manual

#### **Panel Description**



- 1. HDMI In: Connects to HDMI source device.
- 2. HDMI Out: HDMI loop output for HDMI display device connection.
- 3. USB: Connects to laptop, PC or other recording device.
- 4. Audio Out: Connects to headphone for audio de-embedding.
- 5. Audio In: Connects to microphone for audio mixing.

#### System Connection System Requirement

- The recording device with available type-A USB port.
- Microsoft Windows, Mac OS X or Linux.
- HDMI audio/video source with HDMI Cable (Camera, Xbox, PS4, DVD...etc.).

#### System Diagram



#### **Recording for Windows using OBS**

Note: The OBS Player is the first recommended software used for video capturing. Please visit <u>https://obsproject.com/</u> to download the player for Windows, Mac OS X or Linux.

1. Click the "+" icon at "Sources" zone, and then click "Video Capture Device".





2. Type the new device name, and then click "OK" to create new source.



**3.** Select the video capture device and configure the video parameters, and then click "OK".



**4.** Click "Start Recording" at "Controls" zone, and the video and audio recording will start.



5. To stop recording, simply click the "Stop Recording".

**6.** Select "File", and then click "Show Recordings" at the top down menu. The saved recording video file can be found.



7. To configure audio and video parameters, click "Settings" at "Controls" zone.



Settings			$\times$
	Cenara 1		1
General	Sample Rate 44.1 kHz		
"Å" Stream			
📑 Output	Devices		
<b>⊲))</b> Audio			
Video			
	Mic/Auxiliary Audio Mic(USB3.0 HD Audio Capture)		
Hotkeys	Mic/Auxiliary Audio 2 Mic(USB3.0 HD Audio Capture)		
💥 Advanced	Mic/Auxiliary Audio 3 Mic(USB3.0 HD Audio Capture)		
	Mic/Auxiliary Audio 4 Disabled		
	Neters		
	Decay Rate Fast		
	reak Meter Type Sample reak		
	Advanced		
	Monitoring Device Default		
	Disable #indows audio ducking		
	Hotkeys		
	OK Cancel		
			-
Settings			$\times$
Settings	Rase (Canvas) Briolution 1920x1080 Aspect Rat	io <b>16</b> :	×
Settings	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scaled) Resolution 1920x1080 Aspect Rat	io <b>16</b> : io <b>16</b> :	× 9
Settings	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scaled) Resolution 1920x1080 - Aspect Rat Dynascale Filter Bicubic (Sharpened scaling, 16 samples)	io <b>16</b> : io <b>16</b> :	× :9 :9
Settings	Base (Canvas) Resolution 1920x1080 Output (Scaled) Resolution 1920x1080 ~ Aspear Rat Dynacale Filter Bicubic (Sharpened scaling, 16 samples) Common FFS Values 2 60	io <b>16</b> : io <b>16</b> :	× :9 :0
<ul> <li>Settings</li> <li>General</li> <li>(***) Stream</li> <li>(***) Output</li> <li>(*) Audio</li> </ul>	Base (Canvas) Resolution 1920x1080 Output (Sceled) Resolution 1920x1080 ~ Aspect Rat Dynascale Filter Bicubic (Sharpened scaling, 16 samples) Common FFS Values 2 60	io <b>16</b> : io <b>16</b> :	× :9 0
Settings General Gamma Stream Output (*) Audio Video	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Schied) Resolution 1920x1080 ~ Aspect Rat Dynascale Filter Bicubic (Sharpened scaling, 16 samples) Common FFS Values 2 60	io <b>16</b> : io <b>16</b> :	× :9 0
<ul> <li>Settings</li> <li>General</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Sceled) Resolution 1920x1080 ~ Aspect Rat Dynascale Filter Bicubic (Sharpened scaling, 16 samples) Common FFS Values 2 60	io <b>16</b> : io <b>16</b> :	× :9 0
Settings Ceneral (A) Stream Coutput (A) Audio (A) Video (A) Hotkeys	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scried) Resolution 1920x1080 Aspect Rat Bornscale Filter Bicubic (Sharpened scaling, 16 samples) Common FPS Values © 60	io <b>16</b> :	× :9 :0
<ul> <li>Settings</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Socied) Resolution 1920x1080 Aspect Rat Bornscale Filter Bicubic (Sharpened scaling, 16 samples) Common FPS Values 60	io <b>16</b> : io <b>16</b> :	× :9 :9 :0
<ul> <li>Settings</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Schied) Resolution 1920x1080 Aspect Rat Bornscale Filter Bicubic (Sharpened scaling, 16 samples) Common FPS Values C 60	io <b>16</b> : io <b>16</b> :	× :9 :9
<ul> <li>Settings</li> <li>General</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Besolution 1920x1080 Aspect Rat Output (Scried) Resolution 1920x1080 Aspect Rat Donnscale Filter Bicubic (Sharpened scaling, 16 samples) Common FPS Values : 60	io 16:	× :9 :0
<ul> <li>Settings</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scried) Resolution 1920x1080 Aspect Rat Donnscale Filter Bicubic (Sharpened scaling, 16 samples) Common FPS Values : 60	io 16:	× :9 :0 :0
<ul> <li>Settings</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scaled) Resolution 1920x1080 Aspect Rat Downscale Filter Bicubic (Sharpened scaling, 16 samples) Common FFS Values : 60	io 16:	× :9 :0
<ul> <li>Settings</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scaled) Resolution 1920x1080 Aspect Rat Donnscale Filter Bicubic (Sharpened scaling, 16 samples) Common FPS Values 2 60	io 16:	× :9 :9 0 0 0
<ul> <li>Settings</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scaled) Resolution 1920x1080 Aspect Rat Domscale Filter Bicubic (Sharpened scaling, 16 samples) Common FPS Values 2 60	io 16 16	× :9 :9 :0 :0 :0 :0 :0 :0 :0 :0 :0 :0 :0 :0 :0
<ul> <li>Settings</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scaled) Resolution 1920x1080 Aspect Rat Domscale Filter Bicubic (Sharpened scaling, 16 samples) Common FPS Values 2 60	io 16:	× :9 :9 :0
<ul> <li>Settings</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scaled) Resolution 1920x1080 Aspect Rat Domscale Filter Bicubic (Sharpened scaling, 16 samples) Common FFS Values 2 60	io 16:	× :9 :0 :0
<ul> <li>Settings</li> <li>General</li> <li>Stream</li> <li>Output</li> <li>Audio</li> <li>Video</li> <li>Video</li> <li>Hotkeys</li> <li>Advanced</li> </ul>	Base (Canvas) Resolution 1920x1080 Aspect Rat Output (Scaled) Resolution 1920x1080 Aspect Rat Domscale Filter Bicubic (Sharpened scaling, 16 samples) Common FPS Values 2 60	io 16:	× :9 :0 :0

## **Recording for Mac using QuickTime**

The QuickTime Player is the software that comes with Mac PC, it can also be used for video recording.

1. Launch QuickTime Player, click "File" at the top menu and select "New Movie Recording".

100	New Movie Recording New Audio Recording New Screen Recording	て第N ^て第N ^第N	
	Open File Open Location Open Recent	жо жL ►	
	Close Save Duplicate Rename Move To Export Revert To	₩W ₩S ☆₩S	
and the second second	Share	•	

**2.** The recording control panel will appear on the screen, first click the "v" symbol for the drop down menu.

R		
● ● — ●)) ● -:-	V USB3.0 HD Video Capture FaceTime HD Camera	
	Microphone Built-in Microphone: Internal Microphone	
6 CALL	✓ High Maximum	

**3.** Select "USB3.0 HD Video Capture" under "Camera", and select "USB3.0 HD Audio Capture" under "Microphone". Then adjust to desired volume for the speaker.

	<ul> <li>✓ Camera</li> <li>✓ USB3.0 HD Video Capture</li> <li>FaceTime HD Camera</li> </ul>	1
	Microphone Built-in Microphone: Internal Microphone ✓ USB3.0 HD Audio Capture	
6 MARINE	Quality ✓ High Maximum	

4. Click the "Record" button to start recording.



5. To stop recording, simply click the square "Stop" button.



6. Enter the recording file name and select where to save the file.

	Untitled	
Do you wa document Your changes	int to save the changes made to the "Untitled"? s will be lost if you don't save them.	
Export As: Tags:	Untitled	•
Don't Sa	ave Cancel Save	
MANKE	B	

## Recording for Windows using VLC VLC Media Player Initial Setting

The VLC Media Player also can be used for video capturing. Please visit <u>www.videolan.org/vlc/</u> to download VLC Media Player for Windows, Mac OS X or Linux.

For initial use, the hardware accelerated decoding must be set at "Automatic" to ensure the best performance. Please following the instructions below to set the hardware accelerated decoding.

1. Select "Tools", and then click on "Preferences" at the drop down menu.



**2.** Click "Input/Codes", and the select "Automatic" for Hardware-accelerated decoding, and then "Save" to finish the initial VLC setting.

Simple Preferences			
Interface & Audio Video	Subtitles / 05D	Notkeys Codecs Settings	
Codecs			
Mardware-accelerated decoding	Automatic		•
Tast seek			
Video quality post-processing level	6 💿		
Skip M. 264 in-loop deblocking filter	Fone		•
x264 preset and tuning selection	ultrafast	• film	•
x264 profile and level selection	high	• 0	
Optical drive			
Default optical device			•
Files			
Record directory or filename			Browse
Preload MEV files in the same direct	ary		
Danaged or incomplete AVI file	Ask for action		•
Network			
Default caching policy	Custon		•
MTTP promy WRL			
Live555 stream transport	HTTP (default)	ETP over ETSP (TCP)	
Show settings ) Simple () All Reset Freferences		5	ve Cancel

#### **VLC Media Player Direct Show**

1. Select "Media", and then select "Open Capture Device" at the drop down menu.



2. For video device name, select "USB3.0 HD Video Capture".

🛓 Open Media	
🕞 File 📀 Disc 🚏 Network	🖽 Capture Device
Capture mode	DirectShow 💌
Device Selection	
Video device name	Default 🗸
Audio device name	Default Default Integrated Camera Default Default Default
Options	USBS. U AD YI teo Capture
Video size	
	Advanced options
Show more options	Play V Cancel

3. For audio device name, select "Microphone (USB3.0 HD Audio Capture)".

🛓 Open Media	
🕞 File 🔗 Disc 🚏 Network	🖽 Capture Device
Capture mode	DirectShow 🔻
Device Selection	
Video device name	USB3.0 HD Video Capture 🔻
Audio device name	Default 🗸
Options	Default None Microphone (Realter High Definition Au
Video size	Microphone (USBS, U. Hill Audio Capture)
	Advanced options
🔲 Show more options	
	Play V Cancel

4. To set up the correct aspect ratio, click "Advanced options".

🛓 Open Media	
🕞 File 📀 Disc 🚏 Network	🖽 Capture Device
Capture mode	DirectShow 🔻
Device Selection	
Video device name	USB3.0 HD Video Capture 🔻
Audio device name	Microphone(USB3.0 HD Audio Capture) 🔻
Options	
Video size	
	Advanced options
Show more options	
	Flay V Cancel

- 5. Enter the aspect ratio for the video source (e.g. 16:9).
- 6. Click "OK" to exit the "Advanced options" menu.

🛓 Open Me	edia	
🕞 Fil	Advanced Options	8 ×
Captur	Picture aspect-ratio n:m	
- Devi	Video input chroma format	
Video	Video input frame rate	0.00 🜩
Audic	Device properties Tuner properties	E
Opti	Tuner TV Channel	0 束
Video	Tuner Frequency	0 🚖
	Tuner country code	0 🚖
	Video standard	Default -
	Tuner input type	Default -
	Video input pin	-1 -1 -1 -
Show		OK Cancel
		LILAY Cancel

7. Click "Play", the source screen will show in approximately several seconds.

👌 Open Media	
🕑 File 📀 Disc 🚏 Network	🖽 Capture Device
Capture mode	DirectShow 🔻
Device Selection	
Video device name	USB3.0 HD Video Capture 💌
Audio device name	Microphone(USB3.0 HD Audio Capture) 💌
Options	
Video size	
	Advanced options
Show more options	Play Cancel

#### **VLC Media Player Recording**

Note: We recommend using the "Convert/Save" method to record the video from the device for best performance.

1. Select "Media", and then select "Convert / Save" at the dropdown menu.



2. Click "Capture Device" tab on the top right side.

🚖 Open Media	
🕞 File 💊 Disc	Thetwork Capture Device
Capture mode	DirectShow 🔻
Device Selection -	
Video device name	USB3.0 HD Video Capture 🔻
Audio device name	Microphone(USB3.0 HD Audio Capture) 🔻
Options	
Video size	
	Advanced options
Show more options	
	Play V Cancel

 Video device name should be "USB3.0 HD Video Capture" and audio device name should be "Microphone (USB3.0 HD Audio Capture)". **4.** To set the video resolution, type the resolution (e.g. 1920\*1080) at "Video size" textbox.

🛓 Open Media		
🕑 File 📀 Disc 🚏 Network 😇 Capture Device		
Capture mode DirectShow 💌		
Device Selection		
Video device name USB3.0 HD Video Capture 🔻		
Audio device name Microphone (USB3. 0 HD Audio Capture) 🔻		
Options		
Video size 1920*1080		
Advanced options		
Show more options		
Play Cancel		

5. To set the aspect ratio, click "Advanced options".

🛓 Open Media		
🕨 File 💊 Disc 🚏 Network	🥶 Capture Device	
Capture mode	DirectShow 🔻	
Device Selection		
Video device name	USB3.0 HD Video Capture 🔻	
Audio device name	Microphone(USB3.0 HD Audio Capture) 🔻	
Options		
Video size		
	Advanced options	
Show more options		
	Play Cancel	

- 6. Enter the aspect ratio for the video source (e.g. 16:9).
- 7. Click "OK" to exit the "Advanced options" menu.

👌 Open Me	dia	
Fil 4	Advanced Options	? <u>×</u> )
Captur Devi	Ficture aspect-ratio n:m Video input chroma format	
Video	Video input frame rate	0.00 荣
Audio	Device properties Tuner properties	E
-Opti.	Tuner TV Channel	0
Video	Tuner Frequency	0
	Tuner country code	0
	Video standard	Default -
	Tuner input type	Default -
	Video input pin	-1 💌 👻
Show		OK Cancel
C		Converty Dave + Cancel

8. Click "Convert / Save".

🛓 Open Media		
🕞 File 💊 Disc 🚏 Network	🖽 Capture Device	
Capture mode	DirectShow 🔻	
Device Selection		
Video device name	USB3.0 HD Video Capture 💌	
Audio device name	Microphone(USB3.0 HD Audio Capture) 🔻	
Options		
Video size		
	Advanced options	
Show more options	Convert / Save 🔻 Cancel	

9. Select "Display the output" check-box, and set the video format.

🛓 Convert
Source
Type: dshow
Settings © Convert V Display the output Deinterlace Frofile Video - H.264 + MP3 (MP4) Video - M.264 + MP3 (MP4)
Dump raw input           Destination
Destination file: C:\Users\Administrator\Desktop\Movie-2.mp4 Browse Start Cancel

**10.** Then click "Browse" to choose where to save the destination file and enter the file name.

🛓 Convert				
Source				
Source:	dshow: \\			
Type:	dshow			
Setting: Conve Dis Dei: Profi	s ert play the output nterlace ile Video - H 264 + MP3 (MP4) V R ME			
Dump	raw input			
Destination file: C:\Users\Administrator\Desktop\Movie=2.mp4 Browse				
	Start Cancel			

- **11.**Click "Start", and the video and audio recording will start in approximately several seconds.
- **12.** To stop recording, simply click the square "Stop" button at the bottom control panel.





# Specification

Model	BG-CAP-HA		
Description	HDMI to USB Video Capture Device		
Input	(1) HDMI In, (1) Audio In		
Input Connector	(1) Type-A HDMI, (1) 3.5r	nm jack	
Output	(1) HDMI Out, (1) USB, (1	) Audio Out	
Output Connector	(1) Type-A HDMI, (1) Typ	e-A USB, (1) 3.5mm jack	
HDMI Standard	2.0		
HDMI Input Resolution	Up to 4K@60Hz 4:4:4, HDR10		
HDMI Output Resolution	Up to 4K@60Hz 4:4:4, HDR10		
USB Output Color Space	YUV2, RGB		
HDMI Audio Format	LPCM 7.1 audio, Dolby Atmos <sup>®</sup> , Dolby <sup>®</sup> TrueHD, Dolby Digital <sup>®</sup> Plus, DTS:X <sup>™</sup> , and DTS-HD <sup>®</sup> Master Audio <sup>™</sup> pass-through.		
Microphone Audio Format	PCM 2.0		
Headphone Audio Format	PCM 2.0		
OS Support	Windows, Mac OS X, Linux.		
Compatible Media Player	OBS, PotPlayer, VLC and so on.		
	HDMI Source	Captured Video by USB	
	4K@60Hz 4:4:4	1080p@60Hz/720p	
Video Canture Format	1080p@60Hz 4:4:4	1080p@60Hz/720p	
video capture ronnat	720p	720p	
	480	480	
	576	576	
General			
Operation Temperature	-5 to +55°C (+23° to +131°F)		
Storage Temperature	-25 to +70°C (-13° to +158°F)		
Relative Humidity	10% to 90%, Non-condensing		
Dimension (W*H*D)	102mm x 13mm x 61mm		
Net Weight	75g		

#### Warranty

BZBGEAR wants to assure you peace of mind. We're so confident in the quality of our products that along with the manufacturer's one-year limited warranty, we are offering free second-year warranty coverage upon registration\*!

Taking advantage of this program is simple, just follow the steps below:

1. Register your product within 90 days of purchase by visiting BZBGEAR.com/warranty.

2. Complete the registration form. Provide all necessary proof of purchase details, including serial number and a copy of your sales receipt.

For questions, please call 1.888.499.9906 or email support@bzbgear.com.

For complete warranty information, please visit BZBGEAR.com/warranty or scan the QR code below.



\*Terms and conditions apply. Registration is required.

#### **Mission Statement**

BZBGEAR manifests from the competitive nature of the audiovisual industry to innovate while keeping the customer in mind. AV solutions can cost a pretty penny, and new technology only adds to it. We believe everyone deserves to see, hear, and feel the advancements made in today's AV world without having to break the bank. BZBGEAR is the solution for small to medium-sized applications requiring the latest professional products in AV.

We live in a DIY era where resources are abundant on the internet. With that in mind, our team offers system design consultation and expert tech support seven days a week for the products in our BZBGEAR catalog. You'll notice comparably lower prices with BZBGEAR solutions, but the quality of the products is on par with the top brands in the industry. The unparalleled support from our team is our way of showing we care for every one of our customers. Whether you're an integrator, home theater enthusiast, or a do-it-yourselfer, BZBGEAR offers the solutions to allow you to focus on your project and not your budget.