SIEMENS

Data sheet

3RA2210-1DA15-2BB4



Load feeder fuseless, Reversing duty 400 V AC, Size S00 2.20...3.20 A 24 V DC screw terminal for installation on standard mounting rail (also fulfills type of coordination 1) Type of coordination 2, Iq = 150 kA 1 NC (contactor)

product brand name	SIRIUS
product designation	Reversing starter
design of the product	for standard rail or screw mounting
product type designation	3RA22
manufacturer's article number	
 of the supplied contactor 	<u>3RT2015-1BB42</u>
 of the supplied circuit-breakers 	<u>3RV2011-1DA10</u>
 of the supplied link module 	<u>3RA1921-1DA00</u>
General technical data	
size of the circuit-breaker	S00
size of load feeder	S00
insulation voltage with degree of pollution 3 at AC rated value	690 V
surge voltage resistance rated value	6 kV
degree of protection NEMA rating	other
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (switching cycles) of contactor typical	30 000 000
type of assignment	2
type of protection according to ATEX directive 2014/34/EU	Ex II (2) GD
certificate of suitability according to ATEX directive 2014/34/EU	DMT 02 ATEX F 001
Substance Prohibitance (Date)	10/01/2009
Ambient conditions	_
ambient temperature	
 during operation 	-20 +60 °C
 during storage 	-50 +80 °C
during transport	-50 +80 °C
temperature compensation	-20 +60 °C
relative humidity during operation	10 95 %
Main circuit	
number of poles for main current circuit	3
design of the switching contact	electromechanical
adjustable current response value current of the current-dependent overload release	2.2 3.2 A
operating voltage	
 rated value 	690 V
 at AC-3 rated value maximum 	690 V
operating frequency rated value	50 60 Hz

	0.7.4				
operational current at AC-3 at 400 V rated value	2.7 A				
operating power at AC-3					
• at 400 V rated value	1 100 W				
Control circuit/ Control					
type of voltage of the control supply voltage	DC				
control supply voltage at DC					
rated value	24 V				
rated value	24 24 V				
holding power of magnet coil at DC	4 W				
Auxiliary circuit					
product extension auxiliary switch	Yes				
Protective and monitoring functions					
trip class	CLASS 10				
design of the overload release	thermal (bimetallic)				
UL/CSA ratings					
full-load current (FLA) for 3-phase AC motor					
• at 480 V rated value	3.2 A				
yielded mechanical performance [hp]					
for 3-phase AC motor					
— at 200/208 V rated value	0.5 hp				
— at 220/230 V rated value	0.75 hp				
— at 460/480 V rated value	1.5 hp				
— at 575/600 V rated value	2 hp				
Short-circuit protection					
product function short circuit protection	Yes				
design of the short-circuit trip	magnetic				
conditional short-circuit current (Iq)					
 at 400 V according to IEC 60947-4-1 rated value 	150 000 A				
Installation/ mounting/ dimensions					
mounting position	vertical				
mounting position fastening method					
fastening method	vertical screw and snap-on mounting onto 35 mm standard mounting rail 170 mm				
	screw and snap-on mounting onto 35 mm standard mounting rail				
fastening method height	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm				
fastening method height width depth	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm				
fastening method height width depth required spacing	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm				
fastening method height width depth	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm				
fastening method height width depth required spacing • for grounded parts	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm				
fastening method height width depth required spacing • for grounded parts — forwards	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 10 mm 32 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 10 mm 32 mm 0 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards • for live parts — upwards — upwards • upwards	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 32 mm 0 mm 50 mm 50 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — downwards — upwards — at the side — downwards — at the side — upwards — at the side — downwards — upwards — at the side	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — at the side — downwards — forwards — backwards — upwards — downwards — at the side Connections/ Terminals	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — downwards — upwards — at the side — downwards — at the side — upwards — at the side — downwards — upwards — at the side	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 32 mm 0 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — at the side — downwards • for live parts — forwards — a the side — downwards — at the side — downwards — at the side Connections/ Terminals type of electrical connection • for main current circuit	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 32 mm 0 mm 50 mm 10 mm 50 mm 10 mm 50 mm 10 mm 50 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — of orwards — at the side — downwards — at the side — downwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 32 mm 0 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — at the side — downwards • for live parts — forwards — a the side — downwards — at the side — downwards — at the side Connections/ Terminals type of electrical connection • for main current circuit	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 32 mm 0 mm 50 mm 10 mm 50 mm 10 mm 50 mm 10 mm 50 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — backwards — upwards — downwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 10 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm 50 mm 10 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — forwards — downwards • for live parts — forwards — upwards — downwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 10 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — of orwards • for live parts — forwards — backwards — upwards — backwards — upwards — downwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — stranded	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 10 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm 50 mm 10 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — forwards — ownwards • for live parts — ownwards — backwards — upwards — downwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — stranded • at AWG cables for main contacts	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 10 mm 32 mm 0 mm 50 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm 20 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — obackwards — obackwards — ownwards — backwards — backwards — backwards — backwards — backwards — backwards — for auxids — ownwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — stranded • at AWG cables for main contacts connectable conductor cross-section for main contacts	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 10 mm 32 mm 0 mm 50 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm 20 mm 20 mm 10 mm				
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — oforwards • for live parts — forwards — backwards — backwards — backwards — upwards — backwards — backwards — backwards — for auxilis — ownwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — stranded • at AWG cables for main contacts connectable conductor cross-section for main contacts finely stranded with core end processing	screw and snap-on mounting onto 35 mm standard mounting rail 170 mm 90 mm 97 mm 32 mm 0 mm 50 mm 10 mm 10 mm 32 mm 0 mm 50 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm 20 mm 10 mm				

	and rate according to SI		73 %			
touch protection on the front according to IEC 60529		finger-safe, for vertical contact from the front				
Communication/ Prot		_		_	_	
protocol is support			No			
 PROFINET IO PROFIsafe pro 			No No			
	AS-Interface protocol		No			
Certificates/ approva		_				
					For use in hazard-	Declaration of
General Product A	pproval				ous locations	Conformity
(SP)	<u>Confirmation</u>			EHC	K ATEX	UK CA
Declaration of Conformity	Test Certificates			Marine / Shipping		
CE EG-Konf.	<u>Type Test Certific-</u> ates/Test Report	<u>Special Test Cer</u> <u>ate</u>	<u>rtific-</u>	ABS	BUREAU VERITAS	Lloyd's Register us
Marine / Shipping					other	Railway
PRS	RINA			DNV-GL	<u>Confirmation</u>	Vibration and Shock
Dangerous Good						
<u>Transport Informa-</u> tion						
Further information Information- and Downloadcenter (Catalogs, Brochures,) https://www.siemens.com/ic10 Industry Mall (Online ordering system) https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2210-1DA15-2BB4 Cax online generator http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2210-1DA15-2BB4 Service&Support (Manuals, Certificates, Characteristics, FAQs,) https://support.industry.siemens.com/cs/ww/en/ps/3RA2210-1DA15-2BB4 Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros,) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2210-1DA15-2BB4⟨=en Characteristic: Tripping characteristics, I²t, Let-through current https://support.industry.siemens.com/cs/ww/en/ps/3RA2210-1DA15-2BB4/char Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2210-1DA15-2BB4&objecttype=14&gridview=view1						
last modified:			2/16/2	2022 🖸		