## 3RA2120-1BA23-0AP6





Fuseless motor starter Direct start 600VAC Size S0 1.4-2A 220/240VAC 50/60HZ screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ = 150 KA Also full fills type Of coordination 1 1NO+1NC (contactor)

product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
<ul> <li>of the supplied contactor</li> </ul>	3RT2023-1AP60
<ul> <li>of the supplied circuit-breakers</li> </ul>	3RV2011-1BA10
of the supplied link module	3RA2921-1AA00
General technical data	
size of the circuit-breaker	S00
size of load feeder	S0
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (switching cycles) of contactor typical	10 000 000
type of assignment	2
Ambient conditions	
ambient temperature	
during operation	-20 +60 °C
during storage	-50 +80 °C
during transport	-55 +80 °C
Main circuit	
number of poles for main current circuit	3
design of the switching contact	electromechanical
adjustable current response value current of the current-dependent overload release	1.4 2 A
operating voltage	
rated value	690 V
at AC-3 rated value maximum	690 V
operating frequency rated value	50 60 Hz
operational current at AC-3 at 400 V rated value	1.9 A
operating power at AC-3	
• at 400 V rated value	750 W
● at 500 V rated value	750 W
at 690 V rated value	1 100 W
Control circuit/ Control	
control supply voltage at AC	

<ul> <li>at 50 Hz rated value</li> </ul>	220 V
at 50 Hz rated value	176 242 V
<ul> <li>at 60 Hz rated value</li> </ul>	240 V
at 60 Hz rated value	192 264 V
apparent holding power of magnet coil at AC	7.2 VA
inductive power factor with the holding power of the coil	0.28
Auxiliary circuit	
number of NC contacts for auxiliary contacts	1
number of NO contacts for auxiliary contacts	1
Protective and monitoring functions	
trip class	CLASS 10
design of the overload release	thermal (bimetallic)
response value current of instantaneous short-circuit trip unit	26 A
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
• at 480 V rated value	1.63 A
at 600 V rated value	1.72 A
yielded mechanical performance [hp]	
for single-phase AC motor	
— at 230 V rated value	0.13 hp
• for 3-phase AC motor	
— at 460/480 V rated value	0.75 hp
— at 575/600 V rated value	1 hp
Short-circuit protection	
product function short circuit protection	Yes
design of the short-circuit trip	magnetic
conditional short-circuit current (Iq)	magnetic
• at 400 V according to IEC 60947-4-1 rated value	153 000 A
	100 000 71
Installation/ mounting/ dimensions	vertical
Installation/ mounting/ dimensions mounting position	vertical Snap-mounted to DIN rail or screw-mounted with additional push-in lug
Installation/ mounting/ dimensions mounting position fastening method	Snap-mounted to DIN rail or screw-mounted with additional push-in lug
Installation/ mounting/ dimensions mounting position	
Installation/ mounting/ dimensions mounting position fastening method height width	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm
Installation/ mounting/ dimensions mounting position fastening method height width	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm
Installation/ mounting/ dimensions  mounting position fastening method height width depth required spacing • for grounded parts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm
Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm
Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm
Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards — backwards — backwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards — backwards — upwards — upwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm
Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — downwards  — torwards  — downwards  — backwards  — downwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 10 mm
Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — backwards  — backwards  — downwards  • for live parts  — forwards  — backwards  — backwards  — backwards  — at the side  — downwards  — at the side	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 10 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — at the side — downwards — torwards — backwards — backwards — backwards — backwards — at the side Connections/ Terminals	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 10 mm 9 mm 10 mm 9 mm 10 mm 9 mm 10 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards — backwards — a the side — downwards  • for live parts — forwards — backwards — backwards — at the side Connections/ Terminals  type of electrical connection for main current circuit	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 10 mm 9 mm 10 mm 9 mm 10 mm 9 mm 10 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards — backwards — upwards — at the side  Connections/ Terminals  type of electrical connection for main current circuit type of connectable conductor cross-sections	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 0 mm 30 mm 9 mm screw-type terminals  1 10 mm², 2x (2.5 6 mm²)
Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — at the side  Connections/ Terminals  type of electrical connection for main current circuit  type of connectable conductor cross-sections  • for main contacts stranded	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 0 mm 30 mm 9 mm somm 9 mm somm 9 mm somm 9 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards — backwards — upwards — at the side  Connections/ Terminals  type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 0 mm 30 mm 9 mm 10 mm 20 mm 30 mm 10 mm 20 mm 30 mm 20 mm 30 mm 30 mm 30 mm 30 mm 30 mm 40 mm
Installation/ mounting/ dimensions mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards — backwards — upwards — at the side	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 0 mm 30 mm 9 mm 10 mm 20 mm 30 mm 10 mm 20 mm 30 mm 20 mm 30 mm 30 mm 30 mm 30 mm 30 mm 40 mm
Installation/ mounting/ dimensions  mounting position  fastening method height width depth  required spacing	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 0 mm 30 mm 9 mm 10 mm 20 mm 30 mm 10 mm 20 mm 30 mm 20 mm 30 mm 20 mm 30 mm 30 mm 20 mm 30 mm 30 mm 30 mm 30 mm 30 mm
Installation/ mounting/ dimensions  mounting position  fastening method height width depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — a the side  Connections/ Terminals  type of electrical connection for main current circuit  type of connectable conductor cross-sections  • for main contacts stranded  • at AWG cables for main contacts connectable conductor cross-section for main contacts finely stranded with core end processing  Safety related data	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 0 mm 30 mm 9 mm 10 mm 20 mm 30 mm 10 mm 30 mm 10 mm 10 mm 9 mm

protection class IP on the front according to IEC 60529

IP20

touch protection on the front according to IEC 60529 finger

finger-safe, for vertical contact from the front

Certificates/ approvals

**General Product Approval** 

For use in hazardous locations Declaration of Conformity

other

Confirmation







Confirmation

## Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2120-1BA23-0AP6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2120-1BA23-0AP6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2120-1BA23-0AP6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RA2120-1BA23-0AP6&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2120-1BA23-0AP6/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2120-1BA23-0AP6&objecttype=14&gridview=view1

last modified: 12/15/2020 🖸