

Note: This datasheet may be out of date. Please download the latest datasheet of BLM18DN221SH1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLM18DN221SH1%23

## "#" indicates a package specification code.

BLM18DN221SH1#

In Production AEC-Q200 RoHS REACH

< List of part numbers with package codes > BLM18DN221SH1B BLM18DN221SH1D BL


BLM18DN221SH1J



## Applications

Unsuitable	Please be sure to read and comply with
Applications	these "Precautions for use."
	Automotive powertrain/safety equipment,
	Automotive infotainment/comfort
	equipment,Consumer equipment,
	Medical equipment [GHTF A/B/C]
	except for implant & operation & auto-
	dispenser equipment,Industrial
	equipment except for transportation &
Specific	facility & energy equipment
Applications	Please refer to Our Website and
	specifications, etc. for information about
	the performance, functions, quality,
	management, and safety required for
	the above applications, and use
	Products after confirming the
	performance and reliability of the actual
	Product.

# Appearance & Shape



#### (in mm)



# **Packaging Information**

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	1000
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000



## Features

Chip ferrite beads for high frequency noise suppression over a wide frequency range.

### Features

- 1. High impedance characteristic in 1GHz or higher frequency
- 2. High impedance characteristic over a wide frequency band range of 100MHz to 6GHz
- 3. Low DC Resistance enables large Rated Current

### Applications

1. Noise suppression for Automotive LED Lighting.

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# BLM18DN221SH1#

Note: This datasheet may be out of date. Please download the latest datasheet of BLM18DN221SH1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLM18DN221SH1%23

"#" indicates a package specification code.



# Specifications

Shape	SMD
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.15mm
Width	0.8mm
Width Tolerance	±0.15mm
Thickness	0.8mm
Thickness Tolerance	±0.15mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.004g
Number of Circuit	1
Rated Current (at 85°C)	1A
Rated Current (at 125°C)	650mA
DC Resistance(max.)	0.21Ω
Impedance (at 100MHz)	220Ω
Impedance (at 100MHz) Tolerance	±25%
Impedance (at 1GHz)	650Ω
Impedance (at 1GHz) Tolerance	±30%
Size Code (in mm)	1608

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.








# BLM18DN221SH1#

Note: This datasheet may be out of date. Please download the latest datasheet of BLM18DN221SH1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLM18DN221SH1%23


## "#" indicates a package specification code.





In operating temperature exceeding +85°C, derating of current is necessary for this series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics

## Derating of Rated Current

(Resistance element becomes dominant at high frequencies.)

**Equivalent Circuit** 

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

