

## **Micro-RTU Plus**



- Full Electric Power Industry Compliance
- Compact Design for Poletop or Substation Applications
- Protocol Conversions for local IEDs
- Multiple Protocols for SCADA Master and Local IEDs
- Historical Data for all I/O Points
- Units can be Daisy-Chained for Large Point Counts
- TCP/IP (Ethernet) Interface
- Also Available in a Plastic Enclosure
- Custom Applications our Specialty

## **Specifications:**

- Control Sequence: Direct or SBO
- 4 Relay Contacts: Form C, 2 Amps at 30Vdc (resistive load)
- 6 Analog Inputs with twelve-bit resolution, pre-scaled to ± 1 VDC with 0.1% accuracy
- 8 Status Inputs
- Status Input Voltage: 12Vdc to 35Vdc, positive or negative polarity
- Input Current: 0.1ma (typical)
- Isolation: Optical
- Phase-to-Ground 2000V
- Input Voltage: 12Vdc to 35Vdc
- Communication Links: 2 RS-232 Ports, 1 TCP/IP RJ-45 Port
- Available with DNP 3.0, Modbus, PG&E (Data 2179), or Telegyr 8979
- Dimensions: 5.7" x 7"

The Micro-RTUs come with a free copy of the VisiCal software suite that allows it to be configured, calibrated, scanned, monitored or programmed with drag-and-drop and pushbutton simplicity.

🔭 Fisionery RTU Collibration - Micro-RTU / Controller		🎘 Tislonary RTU Calibration - Micro RTU / Centrollier 📰
Di 1540		the take
Executive indexes	Board     Direction     Control     State     State	Bef same KTV independen angen Same KTV     Mill of KTV     Mill of KTV       Approxymen KTV     Mill of KTV     Mill of KTV     Mill of KTV       Same KTV     Mill of KTV     Mill of KTV     Mill of KTV     Mill of KTV       Same KTV     Mill of KTVV     Mill of KTVVV     Mill of KTVVVVVVVVVVVVVVVVVVVVVVVVVVVVVVVVVVVV
Name     Name <th< th=""><td>&gt;):     66: 64: 400 C c1 400 0 0 40 0 46: 65:     Open 0 40 0 40: 60: 65:       (C):     65: 54: 10: 14: 10: 00: 10: 00: 10: 00: 70: 00: 10: 10: 10: 10: 10: 10: 10: 10: 1</td><td>Constant and the second s</td></th<>	>):     66: 64: 400 C c1 400 0 0 40 0 46: 65:     Open 0 40 0 40: 60: 65:       (C):     65: 54: 10: 14: 10: 00: 10: 00: 10: 00: 70: 00: 10: 10: 10: 10: 10: 10: 10: 10: 1	Constant and the second s