## SIEMENS

## Data sheet

## 3RT2015-1BA41



Power contactor, AC-3 7 A, 3 kW / 400 V 1 NO, 12 V DC 3-pole, Size S00 screw terminal

| product brand name  | SIRIUS                     |
|---|----------------------------|
| product designation   | Power contactor            |
| product type designation  | 3RT2                       |
| General technical data  |                            |
| size of contactor   | S00                        |
| product extension   |                            |
| function module for communication   | No                         |
| <ul> <li>auxiliary switch</li> </ul>  | Yes                        |
| power loss [W] for rated value of the current   |                            |
| <ul> <li>at AC in hot operating state</li> </ul>  | 0.6 W                      |
| <ul> <li>at AC in hot operating state per pole</li> </ul>   | 0.2 W                      |
| without load current share typical  | 4 W                        |
| insulation voltage  |                            |
| <ul> <li>of main circuit with degree of pollution 3 rated value</li> </ul>                                  | 690 V                      |
| <ul> <li>of auxiliary circuit with degree of pollution 3 rated value</li> </ul>                             | 690 V                      |
| surge voltage resistance  |                            |
| <ul> <li>of main circuit rated value</li> </ul>   | 6 kV                       |
| <ul> <li>of auxiliary circuit rated value</li> </ul>  | 6 kV                       |
| maximum permissible voltage for safe isolation between<br>coil and main contacts according to EN 60947-1    | 400 V                      |
| shock resistance at rectangular impulse   |                            |
| • at DC   | 6,7g / 5 ms, 4,2g / 10 ms  |
| shock resistance with sine pulse  |                            |
| • at DC   | 10,5g / 5 ms, 6,6g / 10 ms |
| mechanical service life (switching cycles)  |                            |
| <ul> <li>of contactor typical</li> </ul>  | 30 000 000                 |
| <ul> <li>of the contactor with added electronically optimized<br/>auxiliary switch block typical</li> </ul> | 5 000 000                  |
| <ul> <li>of the contactor with added auxiliary switch block<br/>typical</li> </ul>                          | 10 000 000                 |
| reference code according to IEC 81346-2   | Q                          |
| Substance Prohibitance (Date)   | 10/01/2009                 |
| Ambient conditions  |                            |
| installation altitude at height above sea level maximum   | 2 000 m                    |
| ambient temperature   |                            |
| during operation  | -25 +60 °C                 |
| during storage  | -55 +80 °C                 |
| relative humidity minimum   | 10 %                       |
| relative humidity at 55 °C according to IEC 60068-2-30 maximum  | 95 %                       |

| Main circuit  |                     |
|---|---------------------|
| number of poles for main current circuit  | 3                   |
| number of NO contacts for main contacts   | 3                   |
| operating voltage   |                     |
| <ul> <li>at AC-3 rated value maximum</li> </ul>                                       | 690 V               |
| <ul> <li>at AC-3e rated value maximum</li> </ul>                                      | 690 V               |
| operational current   |                     |
| • at AC-1 at 400 V at ambient temperature 40 °C                                       | 18 A                |
| rated value   |                     |
| • at AC-1   | 40.4                |
| — up to 690 V at ambient temperature 40 °C rated value                                | 18 A                |
| — up to 690 V at ambient temperature 60 °C  | 16 A                |
| rated value   |                     |
| • at AC-3   |                     |
| — at 400 V rated value  | 7 A                 |
| — at 500 V rated value  | 6 A                 |
| — at 690 V rated value  | 4.9 A               |
| • at AC-3e  |                     |
| — at 400 V rated value  | 7 A                 |
| — at 500 V rated value  | 6 A                 |
| — at 690 V rated value  | 4.9 A               |
| • at AC-4 at 400 V rated value  | 6.5 A               |
| <ul> <li>at AC-5a up to 690 V rated value</li> </ul>                                  | 15.8 A              |
| <ul> <li>at AC-5b up to 400 V rated value</li> </ul>                                  | 5.8 A               |
| ● at AC-6a  |                     |
| — up to 230 V for current peak value n=20 rated value                                 | 4 A                 |
| — up to 400 V for current peak value n=20 rated value                                 | 4 A                 |
| — up to 500 V for current peak value n=20 rated value                                 | 3.8 A               |
| — up to 690 V for current peak value n=20 rated value                                 | 3.6 A               |
| <ul> <li>at AC-6a</li> <li>— up to 230 V for current peak value n=30 rated</li> </ul> | 2.7 A               |
| value<br>— up to 400 V for current peak value n=30 rated<br>value                     | 2.7 A               |
| — up to 500 V for current peak value n=30 rated value                                 | 2.5 A               |
| — up to 690 V for current peak value n=30 rated value                                 | 2.4 A               |
| minimum cross-section in main circuit at maximum AC-1 rated value                     | 2.5 mm <sup>2</sup> |
| operational current for approx. 200000 operating cycles at AC-4                       |                     |
| • at 400 V rated value  | 2.6 A               |
| at 690 V rated value  | 1.8 A               |
| operational current   |                     |
| • at 1 current path at DC-1   |                     |
| — at 24 V rated value   | 15 A                |
| — at 110 V rated value  | 1.5 A               |
| — at 220 V rated value  | 0.6 A               |
| — at 440 V rated value  | 0.42 A              |
| — at 600 V rated value  | 0.42 A              |
| • with 2 current paths in series at DC-1  |                     |
| — at 24 V rated value   | 15 A                |
| — at 110 V rated value  | 8.4 A               |
| — at 220 V rated value  | 1.2 A               |
| — at 440 V rated value  | 0.6 A               |
| — at 600 V rated value  | 0.5 A               |
| <ul> <li>with 3 current paths in series at DC-1</li> </ul>                            |                     |


| at 24 \/ rated value   | 15 A  |
|--|---|
| — at 24 V rated value  | 15 A<br>15 A  |
| — at 110 V rated value<br>— at 220 V rated value   | 15 A<br>15 A  |
| — at 220 V rated value<br>— at 440 V rated value   | 0.9 A   |
|  | 0.9 A<br>0.7 A  |
| — at 600 V rated value   | 0.7 A   |
| at 1 current path at DC-3 at DC-5  |   |
| — at 24 V rated value  | 15 A  |
| — at 110 V rated value   | 0.1 A   |
| • with 2 current paths in series at DC-3 at DC-5   |   |
| — at 24 V rated value  | 15 A  |
| — at 110 V rated value   | 0.25 A  |
| with 3 current paths in series at DC-3 at DC-5   | 45.4  |
| — at 24 V rated value  | 15 A  |
| — at 110 V rated value   | 15 A  |
| — at 220 V rated value   | 1.2 A   |
| — at 440 V rated value   | 0.14 A  |
| — at 600 V rated value   | 0.14 A  |
| operating power  |   |
| • at AC-2 at 400 V rated value   | 3 kW  |
| • at AC-3  |   |
| — at 230 V rated value   | 1.5 kW  |
| — at 400 V rated value   | 3 kW  |
| — at 500 V rated value   | 3 kW  |
| — at 690 V rated value   | 4 kW  |
| • at AC-3e   |   |
| — at 230 V rated value   | 1.5 kW  |
| — at 400 V rated value   | 3 kW  |
| — at 500 V rated value   | 3 kW  |
| — at 690 V rated value   | 4 kW  |
| operating power for approx. 200000 operating cycles at AC-4  |   |
| • at 400 V rated value   | 1.15 kW   |
| • at 690 V rated value   | 1.15 kW   |
| operating apparent power at AC-6a  |   |
| <ul> <li>up to 230 V for current peak value n=20 rated value</li> </ul>  | 1.5 kVA   |
| <ul> <li>up to 400 V for current peak value n=20 rated value</li> </ul>  | 2.7 kVA   |
| <ul> <li>up to 500 V for current peak value n=20 rated value</li> </ul>  | 3.3 kVA   |
| <ul> <li>up to 690 V for current peak value n=20 rated value</li> </ul>  | 4.3 kVA   |
| operating apparent power at AC-6a  |   |
| <ul> <li>up to 230 V for current peak value n=30 rated value</li> </ul>  | 1 kVA   |
| <ul> <li>up to 400 V for current peak value n=30 rated value</li> </ul>  | 1.8 kVA   |
| <ul> <li>up to 500 V for current peak value n=30 rated value</li> </ul>  | 2.2 kVA   |
| <ul> <li>up to 690 V for current peak value n=30 rated value</li> </ul>  | 2.9 kVA   |
| short-time withstand current in cold operating state   |   |
| <ul> <li>up to 40 °C</li> <li>limited to 1 s switching at zero current maximum</li> </ul>  | 120 A; Use minimum cross-section acc. to AC-1 rated value |
| <ul> <li>limited to 1's switching at zero current maximum</li> <li>limited to 5 s switching at zero current maximum</li> </ul>   | 86 A; Use minimum cross-section acc. to AC-1 rated value  |
| <ul> <li>Initial to 5's switching at zero current maximum</li> <li>limited to 10 s switching at zero current maximum</li> </ul>  | 67 A; Use minimum cross-section acc. to AC-1 rated value  |
| <ul> <li>limited to 10's switching at zero current maximum</li> <li>limited to 30 s switching at zero current maximum</li> </ul> | 52 A; Use minimum cross-section acc. to AC-1 rated value  |
| <ul> <li>Imited to 50's switching at zero current maximum</li> <li>Iimited to 60 s switching at zero current maximum</li> </ul>  | 43 A; Use minimum cross-section acc. to AC-1 rated value  |
| no-load switching frequency  | To A, Ose minimum cross-section acc. to AC-1 fateu value  |
| • at DC  | 10 000 1/h  |
| operating frequency  |   |
| • at AC-1 maximum  | 1 000 1/h   |
| • at AC-2 maximum  | 750 1/h   |
| • at AC-3 maximum  | 750 1/h   |
| • at AC-3e maximum   | 750 1/h   |
| • at AC-4 maximum  | 250 1/h   |
| Control circuit/ Control   |   |
| type of voltage of the control supply voltage  | DC  |
| The or tourage of the control subbilit tourage   |   |


|   | _   |
|---|---|
| control supply voltage at DC  |   |
| rated value   | 12 V  |
| operating range factor control supply voltage rated<br>value of magnet coil at DC |   |
| initial value   | 0.0   |
|   | 0.8   |
| • full-scale value  | _ <u>1.1</u>  |
| closing power of magnet coil at DC  | _ 4 W   |
| holding power of magnet coil at DC  | 4 W   |
| closing delay   | 20 400  |
| • at DC   | 30 100 ms   |
| opening delay   | 7 10 mg   |
| • at DC   | 7 13 ms   |
| arcing time   | 10 15 ms  |
| control version of the switch operating mechanism                                 | Standard A1 - A2  |
| Auxiliary circuit   |   |
| number of NO contacts for auxiliary contacts                                      | 1   |
| instantaneous contact   | 40.4  |
| operational current at AC-12 maximum  | 10 A  |
| operational current at AC-15  | 10.4  |
| at 230 V rated value  | 10 A  |
| at 400 V rated value  | 3 A   |
| at 500 V rated value  | 2 A   |
| at 690 V rated value  | 1 A   |
| operational current at DC-12  |   |
| • at 24 V rated value   | 10 A  |
| • at 48 V rated value   | 6 A   |
| at 60 V rated value   | 6 A   |
| at 110 V rated value  | 3 A   |
| at 125 V rated value  | 2 A   |
| at 220 V rated value  | 1A  |
| at 600 V rated value  | 0.15 A  |
| operational current at DC-13  |   |
| • at 24 V rated value   | 10 A  |
| • at 48 V rated value   | 2 A   |
| at 60 V rated value   | 2 A   |
| at 110 V rated value  | 1A  |
| • at 125 V rated value  | 0.9 A   |
| • at 220 V rated value  | 0.3 A   |
| at 600 V rated value  | 0.1 A   |
| contact reliability of auxiliary contacts   | 1 faulty switching per 100 million (17 V, 1 mA)                   |
| UL/CSA ratings  |   |
| full-load current (FLA) for 3-phase AC motor                                      |   |
| • at 480 V rated value  | 4.8 A   |
| at 600 V rated value  | 6.1 A   |
| yielded mechanical performance [hp]   |   |
| <ul> <li>for single-phase AC motor</li> </ul>                                     |   |
| — at 110/120 V rated value  | 0.25 hp   |
| — at 230 V rated value  | 0.75 hp   |
| <ul> <li>for 3-phase AC motor</li> </ul>  |   |
| — at 200/208 V rated value  | 1.5 hp  |
| — at 220/230 V rated value  | 2 hp  |
| — at 460/480 V rated value  | 3 hp  |
| — at 575/600 V rated value  | 5 hp  |
| contact rating of auxiliary contacts according to UL                              | A600 / Q600   |
| Short-circuit protection  |   |
| design of the fuse link   |   |
| <ul> <li>for short-circuit protection of the main circuit</li> </ul>              |   |
| — with type of coordination 1 required  | gG: 35A (690V,100kA), aM: 20A (690V,100kA), BS88: 35A (415V,80kA) |
| - with type of assignment 2 required  | gG: 20A (690V,100kA), aM: 16A (690V, 100kA), BS88: 20A (415V,     |
|   | 80kA)   |
|   |   |


## • for short-circuit protection of the auxiliary switch required

| Installation/ mounting/ dimensions                           |  |  |  |
|--|--|--|--|
| mounting position  | +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface |  |  |
| fastening method   | screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 60715   |  |  |
| <ul> <li>side-by-side mounting</li> </ul>                    | Yes  |  |  |
| height   | 58 mm  |  |  |
| width  | 45 mm  |  |  |
| depth  | 73 mm  |  |  |
| required spacing   |  |  |  |
| <ul> <li>with side-by-side mounting</li> </ul>               |  |  |  |
| — forwards   | 10 mm  |  |  |
| — upwards  | 10 mm  |  |  |
| — downwards  | 10 mm  |  |  |
| — at the side  | 0 mm   |  |  |
| <ul> <li>for grounded parts</li> </ul>                       |  |  |  |
| — forwards   | 10 mm  |  |  |
| — upwards  | 10 mm  |  |  |
| — at the side  | 6 mm   |  |  |
| — downwards  | 10 mm  |  |  |
| • for live parts   |  |  |  |
| — forwards   | 10 mm  |  |  |
| — upwards  | 10 mm  |  |  |
| — downwards  | 10 mm  |  |  |
| — at the side  | 6 mm   |  |  |
| Connections/ Terminals                                       |  |  |  |
| type of electrical connection                                |  |  |  |
| for main current circuit                                     | screw-type terminals   |  |  |
| <ul> <li>for auxiliary and control circuit</li> </ul>        | screw-type terminals   |  |  |
| at contactor for auxiliary contacts                          | Screw-type terminals   |  |  |
| <ul> <li>of magnet coil</li> </ul>                           | Screw-type terminals   |  |  |
| type of connectable conductor cross-sections                 |  |  |  |
| for main contacts  |  |  |  |
| — solid  | 2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²), 2x 4 mm²  |  |  |
| — solid or stranded  | 2x (0,5 1,5 mm <sup>2</sup> ), 2x (0,75 2,5 mm <sup>2</sup> ), 2x 4 mm <sup>2</sup>  |  |  |
| <ul> <li>finely stranded with core end processing</li> </ul> | 2x (0.5 1.5 mm <sup>2</sup> ), 2x (0.75 2.5 mm <sup>2</sup> )  |  |  |
| at AWG cables for main contacts                              | 2x (20 16), 2x (18 14), 2x 12  |  |  |
| connectable conductor cross-section for main                 |  |  |  |
| contacts   |  |  |  |
| • solid  | 0.5 4 mm²  |  |  |
| stranded   | 0.5 4 mm²  |  |  |
| <ul> <li>finely stranded with core end processing</li> </ul> | 0.5 2.5 mm²  |  |  |
| connectable conductor cross-section for auxiliary            |  |  |  |
| contacts   |  |  |  |
| solid or stranded  | 0.5 4 mm <sup>2</sup>  |  |  |
| <ul> <li>finely stranded with core end processing</li> </ul> | 0.5 2.5 mm²  |  |  |
| type of connectable conductor cross-sections                 |  |  |  |
| <ul> <li>for auxiliary contacts</li> </ul>                   |  |  |  |
| — solid or stranded  | 2x (0.5 1.5 mm <sup>2</sup> ), 2x (0.75 2.5 mm <sup>2</sup> ), 2x 4 mm <sup>2</sup>  |  |  |
| <ul> <li>finely stranded with core end processing</li> </ul> | 2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)  |  |  |
| <ul> <li>at AWG cables for auxiliary contacts</li> </ul>     | 2x (20 16), 2x (18 14), 2x 12  |  |  |
| AWG number as coded connectable conductor cross              |  |  |  |
| section  | 20 12  |  |  |
| for main contacts     for auxiliant contacts                 | 20 12  |  |  |
| for auxiliary contacts                                       | 20 12  |  |  |
| Safety related data  |  |  |  |
| product function   |  |  |  |
| mirror contact according to IEC 60947-4-1                    | Yes; with 3RH29  |  |  |
| B10 value with high demand rate according to SN 31920        | 1 000 000  |  |  |

| proportion of dange   |   |  |   |                               |   |
|---|---|--|---|-------------------------------|---|
|   | nd rate according to SN   |  | 0 %   |                               |   |
| • with high demand rate according to SN 31920<br>failure rate [FIT] with low demand rate according to SN                                      |   |  | 3 %<br>00 FIT   |                               |   |
|   | st interval or service life   | according to 2   | 0 у   |                               |   |
| IEC 61508<br>protection class IP on the front according to IEC  |   | to IEC   | P20   |                               |   |
| 60529   | the front according to  | LEC 60529 fi   | nger-safe, for vertical cont  | act from the front            |   |
| suitability for use   |   |  | nger-sale, for vertical conta                                       |                               |   |
| <ul> <li>safety-related s</li> </ul>  | switching OFF   | Y  | es  |                               |   |
| Certificates/ approva   | 0   |  |   |                               |   |
| General Product A   |   |  |   |                               |   |
| SP<br>SA  |   | <u>Confirmation</u>  | (UL)<br>III   | KC                            | EAC                                     |
| EMC   | Functional<br>Safety/Safety of<br>Machinery                                 | Declaration of C   | onformity   | Test Certificates             |   |
| RCM   | <u>Type Examination</u><br><u>Certificate</u>                               | C C<br>EG-Konf.  |   | Special Test Certific-<br>ate | Type Test Certific-<br>ates/Test Report |
| Marine / Shipping   |   |  |   |                               |   |
| ABS   | BUREAU<br>VERITAS   |  | Llovd's<br>Register<br>us   | PRS                           | RINA                                    |
| Marine / Shipping   | other   |  | Dangerous Good  |                               |   |
| KMRS RMRS   | <u>Confirmation</u>   | UDE VDE  | <u>Transport Informa-</u><br><u>tion</u>                            |                               |   |
| https://www.siemens.<br>Industry Mall (Onlin  | e ordering system)<br>siemens.com/mall/en/en<br>or<br>stion.siemens.com/WW/ | /Catalog/product?m   | spx?lang=en&mlfb=3RT20  | <u>15-1BA41</u>               |   |
| Service&Support (N  | lanuals, Certificates, C<br>ry.siemens.com/cs/ww/                           |  | <u>\41</u>  |                               |   |
| Service&Support (N<br>https://support.indust<br>Image database (pro<br>http://www.automatio<br>Characteristic: Trip<br>https://support.indust | ry.siemens.com/cs/ww/<br>oduct images, 2D dime                              | en/ps/3RT2015-1BA<br>ension drawings, 3<br>:ax_de.aspx?mlfb=3<br>?t, Let-through curr<br>en/ps/3RT2015-1BA | <br>D models, device circuit<br>RT2015-1BA41⟨=en<br>rent<br>∿1/char | diagrams, EPLAN mac           | :ros,)                                  |







last modified:

6/2/2022 🖸