

Ohm Metrics™

Continuous Workstation Monitors - Periodic Verification Unit Model CM420PV

TEST PROCEDURE:

- 1. Unplug the power supply to the CM420 unit.
- 2. Plug the Periodic Verification Unit (PVU) **BENCH** lead (Male Banana Plug) to the common ground at the workstation.
- 3. Connect the PVU GROUND lead (Male Phono Plug) to the CM420 BENCH plug-in.
- 4. Plug the PVU **OPERATOR LEFT** lead (Banana Male Plug) to the CM420 **LEFT OPERATOR** remote jack.
- Plug the PVU OPERATOR RIGHT lead (Banana Male Plug) to the CM420 RIGHT OPERA-TOR remote jack.
- 6. Connect the power supply to the CM420 power plug-in.
- 7. Press the **BENCH** push button on the PVU and the **BENCH** led on the CM420 should change to red, with constant beeps.
- 8. Press the **OPERATOR LEFT** push button on the PVU and the **LEFT OPERATOR** led on the CM420 should change from a blinking red to green.
- Press the OPERATOR RIGHT push button on the PVU and the RIGHT
 OPERATOR led on the CM420 should change from a blinking red to green.
- 10. If the monitor did not pass as per the test procedure call Transforming Technologies at (419) 841-9552



CM420PV Labeled Leads

TEST PROCEDURE: