3RA2220-4AF26-0BB4

Data sheet



Load feeder fuseless, Reversing duty 400 V AC, Size S0 10.0...16.0 A 24 V DC Spring-type terminal for installation on standard mounting rail with standard mounting rail adapter (also fulfills type of coordination 1) Type of coordination 2, Iq = 150 kA 1 NO+1 NC (contactor)

product brand name	SIRIUS
product designation	Reversing starter
design of the product	for standard rail or screw mounting
product type designation	3RA22
manufacturer's article number	
 of the supplied contactor 	3RT2026-2BB40
 of the supplied circuit-breakers 	3RV2021-4AA20
 of the supplied RH assembly kit 	3RA2923-1BB2
 of the supplied link module 	3RA2921-2AA00
General technical data	
size of the circuit-breaker	S0
size of load feeder	S0
insulation voltage with degree of pollution 3 at AC rated value	690 V
surge voltage resistance rated value	6 kV
degree of protection NEMA rating	other
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (switching cycles) of contactor typical	10 000 000
type of assignment	2
type of protection according to ATEX directive 2014/34/EU	Ex II (2) GD
certificate of suitability according to ATEX directive 2014/34/EU	DMT 02 ATEX F 001
Substance Prohibitance (Date)	10/01/2009
Ambient conditions	
ambient temperature	
 during operation 	-20 +60 °C
during storage	-50 +80 °C
during transport	-50 +80 °C
temperature compensation	-20 +60 °C
relative humidity during operation	10 95 %
Main circuit	
number of poles for main current circuit	3
design of the switching contact	electromechanical
adjustable current response value current of the current-dependent overload release	10 16 A
operating voltage	
rated value	690 V
 at AC-3 rated value maximum 	690 V

operating frequency rated value	50 60 Hz
operational current at AC-3 at 400 V rated value	15.5 A
operating power at AC-3	
at 400 V rated value	7 500 W
Control circuit/ Control	
type of voltage of the control supply voltage	DC
control supply voltage at DC	
rated value	24 V
rated value	24 24 V
holding power of magnet coil at DC	5.9 W
Auxiliary circuit	
product extension auxiliary switch	Yes
Protective and monitoring functions	
trip class	CLASS 10
design of the overload release	thermal (bimetallic)
UL/CSA ratings	thermal (billietallie)
full-load current (FLA) for 3-phase AC motor	44.0
• at 480 V rated value	14 A
yielded mechanical performance [hp]	
• for 3-phase AC motor	
— at 220/230 V rated value	5 hp
— at 460/480 V rated value	10 hp
— at 575/600 V rated value	10 hp
Short-circuit protection	
product function short circuit protection	Yes
design of the short-circuit trip	magnetic
conditional short-circuit current (Iq)	
 at 400 V according to IEC 60947-4-1 rated value 	150 000 A
Installation/ mounting/ dimensions	
mounting position	vertical
mounting position fastening method	vertical On adapter for screw and snap-on mounting on 35 mm standard mounting rail
	On adapter for screw and snap-on mounting on 35 mm standard
fastening method	On adapter for screw and snap-on mounting on 35 mm standard mounting rail
fastening method height	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm
fastening method height width	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm
fastening method height width depth	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm
fastening method height width depth required spacing	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm
fastening method height width depth required spacing • for grounded parts	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm
fastening method height width depth required spacing • for grounded parts — forwards	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — backwards	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 10 mm 10 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 0 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards - downwards — downwards — downwards — backwards — backwards — upwards — downwards	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — at the side — downwards • for live parts — forwards — backwards — backwards — upwards — at the side	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 0 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — at the side — downwards — to rewards — backwards — backwards — backwards — upwards — downwards — at the side Connections/ Terminals	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards - at the side — downwards • for live parts — forwards — backwards — upwards — at the side Connections/ Terminals type of electrical connection	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm 10 mm 10 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — torwards — backwards — upwards — torwards — at the side Connections/ Terminals type of electrical connection • for main current circuit	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm 50 mm 50 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — backwards — upwards — torwards — backwards — upwards — at the side Connections/ Terminals type of electrical connection • for auxiliary and control circuit	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm 10 mm 10 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — backwards — upwards — torwards — backwards — backwards — upwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit Safety related data	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 10 mm 50 mm 50 mm 50 mm 50 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — backwards — upwards — backwards — upwards — townwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit Safety related data B10 value with high demand rate according to SN 31920	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 50 mm 10 mm 50 mm 50 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — backwards — upwards — downwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit Safety related data B10 value with high demand rate according to SN 31920 proportion of dangerous failures	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 10 mm 10 mm 10 mm 10 mm 50 mm 10 mm 50 mm 50 mm 10 mm 50 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — backwards — upwards — the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit Safety related data B10 value with high demand rate according to SN 31920 proportion of dangerous failures • with high demand rate according to SN 31920	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 10 mm 50 mm 10 mm 50 mm 10 mm 50 mm 10 mm 10 mm 10 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — backwards — upwards — the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit Safety related data B10 value with high demand rate according to SN 31920 proportion of dangerous failures • with high demand rate according to IEC 60529	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 10 mm 10 mm 10 mm 10 mm 50 mm 10 mm 50 mm 50 mm 10 mm 50 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — backwards — upwards — the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit Safety related data B10 value with high demand rate according to SN 31920 proportion of dangerous failures • with high demand rate according to SN 31920	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 10 mm 50 mm 10 mm 50 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm
fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — backwards — upwards — the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit Safety related data B10 value with high demand rate according to SN 31920 proportion of dangerous failures • with high demand rate according to IEC 60529	On adapter for screw and snap-on mounting on 35 mm standard mounting rail 269 mm 90 mm 130 mm 32 mm 0 mm 50 mm 10 mm 10 mm 10 mm 50 mm 10 mm 50 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm

PROFINET IO protocol	No
PROFIsafe protocol	No
protocol is supported AS-Interface protocol	No

Certificates/ approvals

General Product Approval

For use in hazardous locations

Declaration of Conformity



Confirmation







Declaration of Conformity

Test Certificates

Marine / Shipping



Type Test Certificates/Test Report

Special Test Certificate







Marine / Shipping





Confirmation

other

Vibration and Shock

Railway

Dangerous Good

Transport Information

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2220-4AF26-0BB4

Cax online generator

 $\underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RA2220-4AF26-0BB4}$

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2220-4AF26-0BB4

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2220-4AF26-0BB4&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2220-4AF26-0BB4/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2220-4AF26-0BB4&objecttype=14&gridview=view1

last modified:

2/16/2022

