

WXA2010

2-Channel Hot-Air Station, 200 W (255 W)
Product no.: WXA2010N



Benefits

- › Power unit WXA 2, 2 channels with hot air iron WXHAP 200
- › Best set for hot air tasks
- › Simultaneous operation of 2 soldering tools
- › For operation with external compressed air



Technical Data

| | |
|--|--|
| Dimensions L x W x H (mm) | 174 x 154 x 135 |
| Dimensions L x W x H (inches) | 6,69 x 5,95 x 5,12 |
| Weight (approx.) in kg | 4.0 |
| Voltage | 110 V |
| Power | 200 W (255 W) |
| Channels | 2 |
| Temperature range (depends on tool) °C | 100 - 550 |
| Temperature range (depends on tool) °F | 200 - 999 |
| Temperature accuracy °C | ±9 |
| Temperature accuracy °F | ±17 |
| Temperature stability °C | ±2 |
| Temperature stability °F | ±4 |
| Equipotential bonding socket | Via 3, 5 mm pawl socket on back of device. |
| Display | 255 x 128 dots / Backlighting |
| Air consumption l/min | 20 |
| Operating pressure in bar/psi | 4,00 - 6,00 / 58 - 87 |
| Capacity l/min | 20 |
| Vacuum | --- |