SIEMENS

Data sheet

3RT2016-1BJ81



Power contactor, AC-3 9 A, 4 kW / 400 V 1 NO, 72 V DC 3-pole, Size S00 screw terminal

product brand name	SIRIUS
product brand name product designation	Power contactor
product designation	3RT2
General technical data	SIVIZ
	200
size of contactor	S00
product extension	
function module for communication	No
auxiliary switch	Yes
power loss [W] for rated value of the current	0.011/
at AC in hot operating state	0.9 W
 at AC in hot operating state per pole 	0.3 W
without load current share typical	4 W
insulation voltage	COD)/
 of main circuit with degree of pollution 3 rated value 	690 V
 of auxiliary circuit with degree of pollution 3 rated value 	690 V
surge voltage resistance	
 of main circuit rated value 	6 kV
 of auxiliary circuit rated value 	6 kV
maximum permissible voltage for safe isolation between coil and main contacts according to EN 60947-1	400 V
shock resistance at rectangular impulse	
• at DC	6,7g / 5 ms, 4,2g / 10 ms
shock resistance with sine pulse	
• at DC	10,5g / 5 ms, 6,6g / 10 ms
mechanical service life (switching cycles)	
 of contactor typical 	30 000 000
 of the contactor with added electronically optimized auxiliary switch block typical 	5 000 000
 of the contactor with added auxiliary switch block typical 	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	10/01/2009
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
 during operation 	-25 +60 °C
during storage	-55 +80 °C
relative humidity minimum	10 %
relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %

Main circuit	
number of poles for main current circuit	3
number of NO contacts for main contacts	3
operating voltage	
 at AC-3 rated value maximum 	690 V
 at AC-3e rated value maximum 	690 V
operational current	
 at AC-1 at 400 V at ambient temperature 40 °C rated value 	22 A
• at AC-1	
— up to 690 V at ambient temperature 40 °C rated value	22 A
— up to 690 V at ambient temperature 60 °C rated value	20 A
• at AC-3	
— at 400 V rated value	9 A
— at 500 V rated value	7.7 A
— at 690 V rated value	6.7 A
● at AC-3e	
— at 400 V rated value	9 A
— at 500 V rated value	7.7 A
— at 690 V rated value	6.7 A
• at AC-4 at 400 V rated value	8.5 A
 at AC-5a up to 690 V rated value 	19.4 A
• at AC-5b up to 400 V rated value	7.4 A
• at AC-6a	
 up to 230 V for current peak value n=20 rated value 	5.3 A
 up to 400 V for current peak value n=20 rated value 	5.3 A
— up to 500 V for current peak value n=20 rated value	5.3 A
 up to 690 V for current peak value n=20 rated value 	5 A
 at AC-6a up to 230 V for current peak value n=30 rated value 	3.5 A
 up to 400 V for current peak value n=30 rated value 	3.5 A
 — up to 500 V for current peak value n=30 rated value 	3.6 A
— up to 690 V for current peak value n=30 rated value	3.3 A
minimum cross-section in main circuit at maximum AC-1 rated value operational current for approx. 200000 operating	4 mm ²
cycles at AC-4	
at 400 V rated value	4.1 A
• at 690 V rated value	3.3 A
operational current	
• at 1 current path at DC-1	
— at 24 V rated value	20 A
— at 110 V rated value	2.1 A
— at 220 V rated value	0.8 A
— at 440 V rated value	0.6 A
— at 600 V rated value	0.6 A
with 2 current paths in series at DC-1	
- at 24 V rated value	20 A
	20 A 12 A
— at 110 V rated value	
— at 220 V rated value	1.6 A
— at 440 V rated value	0.8 A
— at 600 V rated value	0.7 A
 with 3 current paths in series at DC-1 	


at 04 V/ material scalars	20.4
— at 24 V rated value	20 A
— at 110 V rated value	20 A
— at 220 V rated value	20 A
— at 440 V rated value	1.3 A
— at 600 V rated value	1 A
• at 1 current path at DC-3 at DC-5	
— at 24 V rated value	20 A
— at 110 V rated value	0.1 A
 with 2 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	20 A
— at 110 V rated value	0.35 A
 with 3 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	20 A
— at 110 V rated value	20 A
— at 220 V rated value	1.5 A
— at 440 V rated value	0.2 A
— at 600 V rated value	0.2 A
operating power	
 at AC-2 at 400 V rated value 	4 kW
• at AC-3	
— at 230 V rated value	2.2 kW
— at 400 V rated value	4 kW
— at 500 V rated value	4 kW
— at 690 V rated value	5.5 kW
• at AC-3e	
— at 230 V rated value	2.2 kW
— at 400 V rated value	4 kW
— at 500 V rated value	4 kW
— at 690 V rated value	5 kW
operating power for approx. 200000 operating cycles at AC-4	
at 400 V rated value	2 kW
at 400 V rated value	2.5 kW
operating apparent power at AC-6a	2.5 KW
up to 230 V for current peak value n=20 rated value	2 kVA
• up to 400 V for current peak value n=20 rated value	3.6 kVA
• up to 500 V for current peak value n=20 rated value	4.6 kVA
• up to 690 V for current peak value n=20 rated value	5.9 kVA
operating apparent power at AC-6a	0.0 KVA
• up to 230 V for current peak value n=30 rated value	1.3 kVA
• up to 400 V for current peak value n=30 rated value	2.4 kVA
 up to 500 V for current peak value n=30 rated value 	3.1 kVA
 up to 690 V for current peak value n=30 rated value 	4 kVA
short-time withstand current in cold operating state	
up to 40 °C	
 limited to 1 s switching at zero current maximum 	155 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 5 s switching at zero current maximum 	111 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 10 s switching at zero current maximum 	86 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 30 s switching at zero current maximum 	66 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 60 s switching at zero current maximum 	55 A; Use minimum cross-section acc. to AC-1 rated value
no-load switching frequency	
• at DC	10 000 1/h
operating frequency	
• at AC-1 maximum	1 000 1/h
• at AC-2 maximum	750 1/h
• at AC-3 maximum	750 1/h
• at AC-3e maximum	750 1/h
• at AC-4 maximum	250 1/h
Control circuit/ Control	
type of voltage of the control supply voltage	DC


control oursely voltage at DC	
control supply voltage at DC rated value 	72 V
	12 V
operating range factor control supply voltage rated value of magnet coil at DC	
• initial value	0.8
• full-scale value	1.1
closing power of magnet coil at DC	4 W
holding power of magnet coil at DC	4 W
closing delay	
• at DC	30 100 ms
opening delay	
• at DC	7 13 ms
arcing time	10 15 ms
control version of the switch operating mechanism	Standard A1 - A2
Auxiliary circuit	
	1
number of NO contacts for auxiliary contacts instantaneous contact	1
operational current at AC-12 maximum	10 A
operational current at AC-15	
at 230 V rated value	10 A
at 200 V rated value	3 A
at 500 V rated value	2 A
at 690 V rated value	1A
operational current at DC-12	
at 24 V rated value	10 A
at 48 V rated value	6 A
at 60 V rated value	6 A
at 110 V rated value	3 A
at 125 V rated value	2 A
at 220 V rated value	1A
at 600 V rated value	0.15 A
operational current at DC-13	
at 24 V rated value	10 A
• at 48 V rated value	2 A
at 40 V rated value	2 A
• at 110 V rated value	1 A
at 125 V rated value	0.9 A
at 220 V rated value	0.3 A
at 500 V rated value	0.1 A
contact reliability of auxiliary contacts	1 faulty switching per 100 million (17 V, 1 mA)
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	7.6.4
 at 480 V rated value at 600 V rated value 	7.6 A 9 A
yielded mechanical performance [hp]	38
 for single-phase AC motor — at 110/120 V rated value 	0.33 hp
— at 230 V rated value	
for 3-phase AC motor	1 hp
	2 hp
— at 200/208 V rated value — at 220/230 V rated value	2 hp 3 hp
	3 hp
— at 460/480 V rated value — at 575/600 V rated value	5 hp 7 5 hp
	7.5 hp A600 / Q600
contact rating of auxiliary contacts according to UL	
Short-circuit protection	
design of the fuse link	
 for short-circuit protection of the main circuit 	
 — with type of coordination 1 required with type of coordination 2 required 	gG: 35A (690V,100kA), aM: 20A (690V,100kA), BS88: 35A (415V,80kA)
— with type of assignment 2 required	gG: 20A (690V,100kA), aM: 16A (690V, 100kA), BS88: 20A (415V, 80kA)
	· · · · · · · · · · · · · · · · · · ·


• for short-circuit protection of the auxiliary switch required

Installation/ mounting/ dimensions	
mounting position	+/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface
fastening method	screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 60715
 side-by-side mounting 	Yes
height	58 mm
width	45 mm
depth	73 mm
required spacing	
 with side-by-side mounting 	
— forwards	10 mm
— upwards	10 mm
— downwards	10 mm
— at the side	0 mm
 for grounded parts 	
— forwards	10 mm
— upwards	10 mm
— at the side	6 mm
— downwards	10 mm
• for live parts	
— forwards	10 mm
— upwards	10 mm
— downwards	10 mm
— at the side	6 mm
Connections/ Terminals	
type of electrical connection	
for main current circuit	screw-type terminals
 for auxiliary and control circuit 	screw-type terminals
at contactor for auxiliary contacts	Screw-type terminals
 of magnet coil 	Screw-type terminals
type of connectable conductor cross-sections	
for main contacts	
— solid	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²), 2x 4 mm²
— solid or stranded	2x (0,5 1,5 mm ²), 2x (0,75 2,5 mm ²), 2x 4 mm ²
 finely stranded with core end processing 	2x (0.5 1.5 mm ²), 2x (0.75 2.5 mm ²)
at AWG cables for main contacts	2x (20 16), 2x (18 14), 2x 12
connectable conductor cross-section for main	
contacts	
• solid	0.5 4 mm²
stranded	0.5 4 mm²
 finely stranded with core end processing 	0.5 2.5 mm²
connectable conductor cross-section for auxiliary	
contacts	
solid or stranded	0.5 4 mm ²
 finely stranded with core end processing 	0.5 2.5 mm²
type of connectable conductor cross-sections	
 for auxiliary contacts 	
— solid or stranded	2x (0.5 1.5 mm ²), 2x (0.75 2.5 mm ²), 2x 4 mm ²
 finely stranded with core end processing 	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
 at AWG cables for auxiliary contacts 	2x (20 16), 2x (18 14), 2x 12
AWG number as coded connectable conductor cross	
section	20 12
for main contacts for auxiliant contacts	20 12
for auxiliary contacts	20 12
Safety related data	
product function	
mirror contact according to IEC 60947-4-1	Yes; with 3RH29
B10 value with high demand rate according to SN 31920	1 000 000

proportion of dange					
	erous failures				
	nd rate according to SN		40 %		
-	nd rate according to SN		73 %		
31920	low demand rate accord		100 FIT		
T1 value for proof tes IEC 61508	t interval or service life	according to 2	20 у		
protection class IP of 60529	on the front according	g to IEC	P20		
touch protection on	the front according to	o IEC 60529	inger-safe, for vertical conta	act from the front	
suitability for use					
 safety-related s 	•		Yes		
Certificates/ approval	S				
General Product Ap	oproval				
() E		Confirmation		<u>KC</u>	EHC
EMC	Functional Safety/Safety of Machinery	Declaration of (Conformity	Test Certificates	
	<u>Type Examination</u> <u>Certificate</u>	UK CA	CE EG-Konf.	Type Test Certific- ates/Test Report	<u>Special Test Certific-</u> <u>ate</u>
Marine / Shipping					
Marine / Shipping	B UREAU VERITAS		Lloyd's Register Lits	PRS	RINA
Marine / Shipping	BUREAU VERITAS	J Å DNV	Lloyds Register LRS Dangerous Good	PRS	RINA
ABS	Other			PRS	RINA
Marine / Shipping	Confirmation wnloadcenter (Catalo com/ic10	UDE VDE	Dangerous Good Transport Informa- tion	PRS	EINA
Marine / Shipping Marine / Shipping Eurther information Information- and Do https://www.siemens. Industry Mall (Onlin https://mall.industry.s	Confirmation confirmation winloadcenter (Catalo com/ic10 e ordering system) iemens.com/mall/en/en	vDE vDE	Dangerous Good Transport Informa- tion	PRS	EINA
Marine / Shipping Marine / Shipping	Confirmation wwnloadcenter (Catalo com/ic10 e ordering system) iemens.com/mall/en/en or tion.siemens.com/WW/	ogs, Brochures,)	Dangerous Good <u>Transport Informa-</u> <u>tion</u> hlfb=3RT2016-1BJ81 uspx?lang=en&mlfb=3RT20	E-1BJ81	RINA
Marine / Shipping Marine / Shipping Wither information Information- and Do https://www.siemens. Industry Mall (Onlin https://mall.industry.s Cax online generato http://support.automa Service&Support (M	Confirmation confirmation wwnloadcenter (Catalo com/ic10 e ordering system) iemens.com/mall/en/en or ition.siemens.com/WW// lanuals, Certificates, C	rgs, Brochures,) //Catalog/product?m //CAXorder/default.a Characteristics, FA	Dangerous Good <u>Transport Informa-</u> <u>tion</u> hlfb=3RT2016-1BJ81 uspx?lang=en&mlfb=3RT20 AQs,)	E 16-1BJ81	KINA
Marine / Shipping Marine / Shipping Marine / Shipping Marine / Shipping Marine / Shipping Marine / Shipping Further information Information- and Do https://www.siemens. Industry Mall (Onlin https://support.automa Service&Support (M https://support.industry	Confirmation winloadcenter (Catalo com/ic10 e ordering system) iemens.com/mall/en/en or tion.siemens.com/WW// lanuals, Certificates, C ry.siemens.com/cs/ww/	rgs, Brochures,) //Catalog/product?m //CAXorder/default.a Characteristics, F/ /en/ps/3RT2016-1B	Dangerous Good <u>Transport Informa-</u> <u>tion</u> hlfb=3RT2016-1BJ81 uspx?lang=en&mlfb=3RT20 AQs,) J81		ECTOS)
Marine / Shipping Marine / Shipping Wither information Information- and Do https://www.siemens. Industry Mall (Onlin https://mall.industry.si Cax online generato http://support.automa Service&Support (M https://support.indust Image database (pro http://www.automatio	Confirmation wwnloadcenter (Catalo com/ic10 e ordering system) iemens.com/mall/en/en or tion.siemens.com/WW// lanuals, Certificates, C ry.siemens.com/cs/ww// oduct images, 2D dimens.com/bilddb/co	vps, Brochures,) //Catalog/product?m //Catalog/product?m //CAXorder/default.a Characteristics, F/ /en/ps/3RT2016-1B ension drawings, i cax_de.aspx?mlfb=	Dangerous Good <u>Transport Informa-</u> <u>tion</u> hlfb=3RT2016-1BJ81 aspx?lang=en&mlfb=3RT20 AQs,) J81 3D models, device circuit 3RT2016-1BJ81⟨=en		acros,)
Marine / Shipping Marine / Shipping	Confirmation Confirmation winloadcenter (Catalo com/ic10 e ordering system) iemens.com/mall/en/en or tion.siemens.com/WW// lanuals, Certificates, C ry.siemens.com/cs/ww// oduct images, 2D dimension n.siemens.com/bilddb/co ping characteristics, If	rgs, Brochures,) A/Catalog/product?n //Catalog/product?n //CAXorder/default.a Characteristics, F/A /en/ps/3RT2016-1B ension drawings, i cax_de.aspx?mlfb= 2 ² t, Let-through cur	Dangerous Good <u>Transport Informa-</u> <u>tion</u> hlfb=3RT2016-1BJ81 aspx?lang=en&mlfb=3RT20 AQs,) J81 3D models, device circuit 3RT2016-1BJ81⟨=en rent		Acros,)
Marine / Shipping Marine / Shipping	Confirmation wwnloadcenter (Catalo com/ic10 e ordering system) iemens.com/mall/en/en or tion.siemens.com/WW// lanuals, Certificates, C ry.siemens.com/cs/ww// oduct images, 2D dimens.com/bilddb/co	rgs, Brochures,) A/Catalog/product?n //Catalog/product?n //CAXorder/default.a Characteristics, F/A /en/ps/3RT2016-1B ension drawings, cax_de.aspx?mlfb= 2 ⁴ t, Let-through cur /en/ps/3RT2016-1B	Dangerous Good <u>Transport Informa-</u> <u>tion</u> hlfb=3RT2016-1BJ81 aspx?lang=en&mlfb=3RT20 AQs,) J81 3D models, device circuit 3RT2016-1BJ81⟨=en rent J81/char		ecros,)







last modified:

6/2/2022 🖸