3RT2027-4XB40-0LA2

Data sheet



Traction contactor, AC-3 32 A, 15 kW / 400 V 1 NO + 1 NC with solid-state operating mechanism 24 V DC, 0.7-1.25* Us with integrated varistor 3-pole, size S0 ring cable lug connection

product brand name	SIRIUS	
product designation	Contactor	
design of the product	With extended operating range	
product type designation	3RT2	
General technical data		
size of contactor	S0	
product extension		
 function module for communication 	No	
auxiliary switch	Yes	
power loss [W] for rated value of the current		
 at AC in hot operating state 	8.1 W	
 at AC in hot operating state per pole 	2.7 W	
 without load current share typical 	0.8 W	
insulation voltage		
 of main circuit with degree of pollution 3 rated value 	690 V	
 of auxiliary circuit with degree of pollution 3 rated value 	690 V	
surge voltage resistance		
 of main circuit rated value 	6 kV	
 of auxiliary circuit rated value 	6 kV	
maximum permissible voltage for safe isolation between coil and main contacts according to EN 60947-1	400 V	
shock resistance at rectangular impulse		
• at DC	10g / 5 ms, 7,5g / 10 ms	
shock resistance with sine pulse		
• at DC	15g / 5 ms, 10g / 10 ms	
mechanical service life (switching cycles)		
 of contactor typical 	10 000 000	
 of the contactor with added electronically optimized auxiliary switch block typical 	5 000 000	
of the contactor with added auxiliary switch block typical	10 000 000	
reference code according to IEC 81346-2	Q	
Substance Prohibitance (Date)	10/01/2009	
Ambient conditions		
installation altitude at height above sea level maximum	2 000 m	
ambient temperature		
 during operation 	-40 +70 °C	
during storage	-55 +80 °C	
relative humidity minimum	10 %	

relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %	
lain circuit		
number of poles for main current circuit	3	
number of NO contacts for main contacts	3	
operating voltage		
at AC-3 rated value maximum	690 V	
 at AC-3e rated value maximum 	690 V	
operational current		
 at AC-1 at 400 V at ambient temperature 40 °C rated value 	50 A	
• at AC-1		
— up to 690 V at ambient temperature 40 °C rated value	50 A	
 up to 690 V at ambient temperature 60 °C rated value 	42 A	
at AC-2 at 400 V rated value	32 A	
• at AC-3		
— at 400 V rated value	32 A	
— at 500 V rated value	32 A	
— at 690 V rated value	21 A	
• at AC-3e	22 A	
— at 400 V rated value — at 500 V rated value	32 A 32 A	
— at 500 V rated value — at 690 V rated value	21 A	
at AC-4 at 400 V rated value	22 A	
minimum cross-section in main circuit		
at maximum AC-1 rated value	10 mm²	
at maximum Ith rated value	10 mm²	
operational current for approx. 200000 operating cycles at AC-4	10 11111	
at 400 V rated value	12 A	
• at 690 V rated value	12 A	
operating power		
 at AC-2 at 400 V rated value 	15 kW	
• at AC-3		
— at 230 V rated value	7.5 kW	
— at 400 V rated value	15 kW	
— at 500 V rated value	15 kW	
— at 690 V rated value	18.5 kW	
• at AC-3e		
— at 230 V rated value	7.5 kW	
— at 400 V rated value	15 kW	
— at 500 V rated value	15 kW	
— at 690 V rated value	18.5 kW	
operating power for approx. 200000 operating cycles at AC-4		
at 400 V rated value	6 kW	
at 690 V rated value	10.3 kW	
short-time withstand current in cold operating state up to 40 °C	400 A 11	
limited to 1 s switching at zero current maximum	499 A; Use minimum cross-section acc. to AC-1 rated value	
limited to 5 s switching at zero current maximum	395 A; Use minimum cross-section acc. to AC-1 rated value	
limited to 10 s switching at zero current maximum	260 A; Use minimum cross-section acc. to AC-1 rated value	
limited to 30 s switching at zero current maximum	186 A; Use minimum cross-section acc. to AC-1 rated value	
Iimited to 60 s switching at zero current maximum	152 A; Use minimum cross-section acc. to AC-1 rated value	
no-load switching frequency	4 500 4/1-	
• at DC	1 500 1/h	
operating frequency	750.1/b	
• at AC 3 requireurs	750 1/h	
• at AC-2 maximum	750 1/h	
at AC-3 maximum	750 1/h	

	750.4/
at AC-3e maximum	750 1/h
at AC-2 at AC-3e maximum	750 1/h
• at AC-4 maximum	250 1/h
Ratings for railway applications	
thermal current (Ith) up to 690 V	
 up to 40 °C according to IEC 60077 rated value 	50 A
up to 70 °C according to IEC 60077 rated value	36 A
Control circuit/ Control	
type of voltage	DC
type of voltage of the control supply voltage	DC
control supply voltage at DC	
rated value	24 V
operating range factor control supply voltage rated	
value of magnet coil at DC	
• initial value	0.7
• full-scale value	1.25
design of the surge suppressor	with varistor
inrush current peak	3 A
duration of inrush current peak	_ 30 µs
locked-rotor current mean value	_ 0.3 A
locked-rotor current peak	0.52 A
duration of locked-rotor current	180 ms
holding current mean value	45 mA
closing power of magnet coil at DC	6.7 W
holding power of magnet coil at DC	1.4 W
closing delay	
• at DC	50 75 ms
opening delay	
• at DC	30 50 ms
arcing time	10 10 ms Standard A1 - A2
control version of the switch operating mechanism	Standard AT - AZ
Auxiliary circuit	
Auxiliary circuit number of NC contacts for auxiliary contacts	1
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact	1 1
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact number of NO contacts for auxiliary contacts	1 1 1
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact number of NO contacts for auxiliary contacts • instantaneous contact	1 1 1 1
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact number of NO contacts for auxiliary contacts • instantaneous contact operational current at AC-12 maximum	1 1 1
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact number of NO contacts for auxiliary contacts • instantaneous contact operational current at AC-12 maximum operational current at AC-15	1 1 1 1 10 A
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact number of NO contacts for auxiliary contacts • instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value	1 1 1 1 1 10 A
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact number of NO contacts for auxiliary contacts • instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value	1 1 1 1 10 A 10 A 3 A
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact number of NO contacts for auxiliary contacts • instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value	1 1 1 1 10 A 10 A 3 A 2 A
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact number of NO contacts for auxiliary contacts • instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value	1 1 1 1 10 A 10 A 3 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value operational current at DC-12	1 1 1 1 10 A 10 A 3 A 2 A 1 A
Auxiliary circuit number of NC contacts for auxiliary contacts • instantaneous contact number of NO contacts for auxiliary contacts • instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value operational current at DC-12 • at 24 V rated value	1 1 1 1 1 1 10 A 10 A 3 A 2 A 1 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value at 690 V rated value at 24 V rated value at 24 V rated value at 48 V rated value	1 1 1 1 10 A 10 A 3 A 2 A 1 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 60 V rated value at 60 V rated value at 60 V rated value	1 1 1 1 10 A 10 A 3 A 2 A 1 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 48 V rated value at 60 V rated value at 60 V rated value at 110 V rated value	1 1 1 1 10 A 10 A 3 A 2 A 1 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 60 V rated value at 60 V rated value at 60 V rated value at 110 V rated value at 125 V rated value	1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 3 A 2 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 48 V rated value at 60 V rated value at 60 V rated value at 110 V rated value at 125 V rated value at 220 V rated value	1 1 1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A 1 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 60 V rated value at 110 V rated value at 125 V rated value at 220 V rated value at 600 V rated value	1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 3 A 2 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 48 V rated value at 110 V rated value at 125 V rated value at 220 V rated value at 600 V rated value at 600 V rated value at 600 V rated value operational current at DC-13	1 1 1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 3 A 2 A 1 A 0.15 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 60 V rated value at 110 V rated value at 125 V rated value at 220 V rated value at 600 V rated value	1 1 1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A 1 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 60 V rated value at 110 V rated value at 125 V rated value at 220 V rated value at 600 V rated value	1 1 1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 7 A 7 A 7 A 7 A 7 A 7 A 7 A 7 A 7 A 7
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 60 V rated value at 110 V rated value at 125 V rated value at 220 V rated value at 600 V rated value at 600 V rated value at 600 V rated value at 24 V rated value operational current at DC-13 at 24 V rated value at 48 V rated value at 60 V rated value at 60 V rated value at 60 V rated value	1 1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 7 A 7 A 7 A 7 A 7 A 7 A 7 A 7 A 7 A 7
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 110 V rated value at 125 V rated value at 220 V rated value at 24 V rated value at 25 V rated value at 27 V rated value at 28 V rated value at 29 V rated value at 29 V rated value at 29 V rated value at 48 V rated value at 49 V rated value	1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A 1 A 0.15 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 690 V rated value operational current at DC-12 at 24 V rated value at 48 V rated value at 110 V rated value at 125 V rated value at 600 V rated value at 220 V rated value at 600 V rated value	1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A 1 A 0.15 A 10 A 2 A 2 A 1 A 0.19 A
number of NC contacts for auxiliary contacts	1 1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 3 A 2 A 1 A 0.15 A 10 A 2 A 2 A 1 A 0.9 A 0.3 A
number of NC contacts for auxiliary contacts	1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A 1 A 0.15 A 10 A 2 A 2 A 1 A 0.19 A
number of NC contacts for auxiliary contacts	1 1 1 1 1 10 A 10 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 3 A 2 A 1 A 0.15 A 10 A 2 A 2 A 1 A 0.9 A 0.3 A

 at 480 V rated value 	27 A		
at 600 V rated value	27 A		
yielded mechanical performance [hp]			
 for single-phase AC motor 			
 — at 110/120 V rated value 	2 hp		
— at 230 V rated value	5 hp		
 for 3-phase AC motor 			
 at 200/208 V rated value 	10 hp		
 at 220/230 V rated value 	10 hp		
 at 460/480 V rated value 	20 hp		
— at 575/600 V rated value	25 hp		
contact rating of auxiliary contacts according to UL	A600 / Q600		
Short-circuit protection			
product function short circuit protection	No		
design of the fuse link			
 for short-circuit protection of the main circuit 			
 — with type of coordination 1 required 	gG: 125A (690V,100kA), aM: 50A (690V,100kA), BS88: 125A		
	(415V,80kA)		
 — with type of assignment 2 required 	gG: 50A (690V,100kA), aM: 25A (690V, 100kA), BS88: 50A (415V,		
	80kA)		
 for short-circuit protection of the auxiliary switch required 	gG: 10 A (500 V, 1 kA)		
Installation/ mounting/ dimensions	1/190° retation possible or visiting becoming a sufficient security		
mounting position	+/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface		
fastening method	screw and snap-on mounting onto 35 mm standard mounting rail		
idotoming motifod	according to DIN EN 60715		
 side-by-side mounting 	Yes		
height	91 mm		
width	45 mm		
depth	107 mm		
required spacing			
 with side-by-side mounting 			
— forwards	10 mm		
— upwards	10 mm		
— downwards	10 mm		
— at the side	0 mm		
 for grounded parts 			
— forwards	10 mm		
— upwards	10 mm		
— at the side	6 mm		
— downwards	10 mm		
• for live parts			
— forwards	10 mm		
— upwards	10 mm		
— downwards	10 mm		
— at the side	6 mm		
Connections/ Terminals			
type of electrical connection			
for main current circuit	Ring cable lug connection		
for auxiliary and control circuit	ring terminal lug connection		
at contactor for auxiliary contacts	Ring cable lug connection		
of magnet coil	Ring cable lug connection		
Safety related data	<u></u>		
product function			
•	Vge		
mirror contact according to IEC 60947-4-1 positively driven operation according to IEC 60047.	Yes		
 positively driven operation according to IEC 60947- 	No		
5-1			
	450 000		
B10 value with high demand rate according to SN 31920	450 000		
	450 000 40 %		

 with high demand rate according to SN 31920 	73 %
failure rate [FIT] with low demand rate according to SN 31920	100 FIT
T1 value for proof test interval or service life according to IEC 61508	20 y
protection class IP on the front according to IEC 60529	IP00
Communication/ Protocol	
product function bus communication	No
Certificates/ approvals	

General Product Approval





Confirmation



<u>KC</u>



EMC Functional Safety/Safety of Machinery	Declaration of Conformity	Test Certificates
---	---------------------------	-------------------



Type Examination Certificate





Type Test Certificates/Test Report

Special Test Certific-<u>ate</u>

Marine / Shipping













Marine / Shipping **Dangerous Good** other Railway



Confirmation



Type Test Certificates/Test Report

Vibration and Shock

Transport Informa-<u>tion</u>

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT2027-4XB40-0LA2

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT2027-4XB40-0LA2

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RT2027-4XB40-0LA2

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)


http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RT2027-4XB40-0LA2&lang=en


Characteristic: Tripping characteristics, I²t, Let-through current


https://support.industry.siemens.com/cs/ww/en/ps/3RT2027-4XB40-0LA2/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT2027-4XB40-0LA2&objecttype=14&gridview=view1







last modified: 2/1/2022 🖸