SIEMENS

Data sheet

3RT2517-1BF40



Power contactor, AC-3 12 A, 5.5 kW / 400 V 2 NO + 2 NC 110 V DC 4-pole Size S00 screw terminals

product brand name	SIRIUS
product designation	contactor
product type designation	3RT25
General technical data	
size of contactor	S00
product extension	
 function module for communication 	No
auxiliary switch	Yes
insulation voltage	
 of main circuit with degree of pollution 3 rated value 	690 V
 of auxiliary circuit with degree of pollution 3 rated value 	690 V
surge voltage resistance	
 of main circuit rated value 	6 kV
of auxiliary circuit rated value	6 kV
maximum permissible voltage for safe isolation between coil and main contacts according to EN 60947-1	400 V
shock resistance at rectangular impulse	
• at DC	7.3g / 5 ms, 4.7g / 10 ms
shock resistance with sine pulse	
• at DC	11,4g / 5 ms, 7,3g / 10 ms
mechanical service life (switching cycles)	
 of contactor typical 	30 000 000
 of the contactor with added electronically optimized auxiliary switch block typical 	5 000 000
 of the contactor with added auxiliary switch block typical 	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	10/01/2009
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
during operation	-25 +60 °C
during storage	-55 +80 °C
relative humidity minimum	10 %
relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %
Main circuit	
number of poles for main current circuit	4
number of NO contacts for main contacts	2

number of NC contacts for main contacts	2		
operational current			
• at AC-1 up to 690 V			
— at ambient temperature 40 °C rated value	22 A		
— at ambient temperature 60 °C rated value	20 A		
• at AC-2 at AC-3 at 400 V	2077		
— per NO contact rated value	12 A		
— per NC contact rated value	9 A		
minimum cross-section in main circuit at maximum AC-1 rated value	4 mm ²		
operational current			
• at 1 current path at DC-1			
— at 24 V rated value	20 A		
— at 110 V rated value	2.1 A		
— at 220 V rated value	0.8 A		
— at 440 V rated value	0.6 A		
with 2 current paths in series at DC-1	0.0 A		
with 2 current paths in series at DC-1 — at 24 V rated value	20 A		
	20 A 12 A		
— at 110 V rated value			
— at 220 V rated value	1.6 A		
— at 440 V rated value	0.8 A		
• at 1 current path at DC-3 at DC-5			
— at 24 V per NC contact rated value	20 A		
— at 24 V per NO contact rated value	20 A		
 — at 110 V per NC contact rated value 	0.075 A		
 — at 110 V per NO contact rated value 	0.15 A		
 — at 220 V per NC contact rated value 	0.375 A		
 — at 220 V per NO contact rated value 	0.75 A		
 with 2 current paths in series at DC-3 at DC-5 			
 — at 24 V per NC contact rated value 	20 A		
 — at 24 V per NO contact rated value 	20 A		
 — at 110 V per NC contact rated value 	0.175 A		
— at 110 V per NO contact rated value	0.35 A		
operating power at AC-2 at AC-3			
 at 230 V per NC contact rated value 	2.2 kW		
 at 230 V per NO contact rated value 	3 kW		
 at 400 V per NC contact rated value 	4 kW		
 at 400 V per NO contact rated value 	5.5 kW		
short-time withstand current in cold operating state up to 40 °C			
 limited to 1 s switching at zero current maximum 	125 A; Use minimum cross-section acc. to AC-1 rated value		
 limited to 5 s switching at zero current maximum 	123 A; Use minimum cross-section acc. to AC-1 rated value		
 limited to 10 s switching at zero current maximum 	96 A; Use minimum cross-section acc. to AC-1 rated value		
 limited to 30 s switching at zero current maximum 	74 A; Use minimum cross-section acc. to AC-1 rated value		
 limited to 60 s switching at zero current maximum 	61 A; Use minimum cross-section acc. to AC-1 rated value		
power loss [W] at AC-3 at 400 V for rated value of the	1.2 W		
operational current per conductor			
no-load switching frequency			
• at AC	10 000 1/h		
• at DC	10 000 1/h		
operating frequency			
• at AC-1 maximum	1 000 1/h		
Control circuit/ Control			
type of voltage of the control supply voltage	DC		
control supply voltage at DC			
rated value	110 V		
operating range factor control supply voltage rated value of magnet coil at DC			
initial value	0.8		
• full-scale value	1.1		
closing power of magnet coil at DC	4 W		

holding power of magnet coil at DC	4 W		
closing delay			
• at DC	30 100 ms		
opening delay	50 100 m5		
• at DC	7 13 ms		
arcing time	10 15 ms		
Auxiliary circuit			
number of NC contacts for auxiliary contacts	0		
instantaneous contact	ů (martine) (mar		
number of NO contacts for auxiliary contacts	0		
instantaneous contact			
operational current at AC-12 maximum	10 A		
operational current at AC-15			
 at 230 V rated value 	10 A		
at 400 V rated value	3 A		
operational current at DC-12			
• at 48 V rated value	6 A		
• at 60 V rated value	6 A		
• at 110 V rated value	3 A		
• at 125 V rated value	2 A		
 at 220 V rated value 	1 A		
at 600 V rated value	0.15 A		
operational current at DC-13			
• at 24 V rated value	10 A		
 at 48 V rated value 	2 A		
 at 60 V rated value 	2 A		
 at 110 V rated value 	1 A		
 at 220 V rated value 	0.3 A		
• at 600 V rated value	0.1 A		
contact reliability of auxiliary contacts	1 faulty switching per 100 million (17 V, 1 mA)		
UL/CSA ratings			
yielded mechanical performance [hp]			
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value	2 hp		
 yielded mechanical performance [hp] for single-phase AC motor at 230 V rated value for 3-phase AC motor at 460/480 V rated value 	2 hp 5 hp		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value			
 yielded mechanical performance [hp] for single-phase AC motor at 230 V rated value for 3-phase AC motor at 460/480 V rated value 	5 hp		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link	5 hp		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit	5 hp A600 / Q600		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA)		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA)		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA)		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA)		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100 kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100 kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm 73 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm 73 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — backwards	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm 73 mm 0 mm 0 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — backwards — upwards	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm 73 mm 0 mm 0 mm 0 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — backwards — upwards — downwards	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm 73 mm 0 mm 0 mm 0 mm 0 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — backwards — upwards — downwards — at the side	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm 73 mm 0 mm 0 mm 0 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — backwards — upwards — at the side • for grounded parts	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm 73 mm 0 mm 0 mm 0 mm 0 mm 0 mm		
yielded mechanical performance [hp] • for single-phase AC motor at 230 V rated value • for 3-phase AC motor at 460/480 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — backwards — upwards — downwards — at the side	5 hp A600 / Q600 gG: 35 A (690 V, 100 kA) gG: 20A (690V, 100kA) fuse gG: 10 A +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 57.5 mm 45 mm 73 mm 0 mm 0 mm 0 mm		

usuerda	1	0			
— upwards		0 mm			
— at the side		6 mm			
— downwards		0 mm			
 for live parts 					
— forwards		0 mm			
— backwards		0 mm			
— upwards		0 mm			
— downwards		0 mm			
— at the side		6 mm			
Connections/ Terminals					
type of electrical connection					
for main current circuit		screw-type terminals			
for auxiliary and control circuit		screw-type terminals			
at contactor for auxiliary contacts		Screw-type terminals			
of magnet coil		Screw-type terminals			
type of connectable conductor cross-sections					
 for main contacts 					
— solid		2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²), 2x 4 mm²			
— solid or stranded		2x (0,5 1,5 mm²), 2x (0,75 2,5 mm²), 2x 4 mm²		2	
 finely stranded with core end processing 	g	2x (0.5 1.5 mm²), 2x (0.75	5 2.5 mm²)		
• at AWG cables for main contacts		2x (20 16), 2x (18 14), 2x 12			
type of connectable conductor cross-sections					
for auxiliary contacts					
— solid		2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²), 2x 4 mm²			
— solid or stranded		2x (0.5 1.5 mm ²), 2x (0.75		-	
— finely stranded with core end processing	g	2x (0.5 1.5 mm ²), 2x (0.75			
			2x (20 16), 2x (18 14), 2x 12		
AWG number as coded connectable conductor cross 20 12 section for main contacts 20 12					
Safety related data					
product function					
 mirror contact according to IEC 60947-4-1 		Yes; with 3RH29			
 positively driven operation according to IEC 5-1 	60947-	No			
T1 value for proof test interval or service life accord IEC 61508	ding to	20 у			
protection class IP on the front according to IE 60529	с	IP20			
touch protection on the front according to IEC 60529		finger-safe, for vertical contact from the front			
Certificates/ approvals					
General Product Approval				EMC	
General Product Approval				EMC	
Confirmation			EAC	RCM	
Functional		_			
Safety/Safety of Declaration of Conformit Machinery	у	Test Certificates		Marine / Shipping	
Safety/Safety of Declaration of Conformit	у	Test Certificates Special Test Certificates ate	<u>Type Test Certific-</u> ates/Test Report	Marine / Shipping	













other





Transport Informa-<u>tion</u>

Dangerous Good

Further information

Information- and Downloadcenter (Catalogs, Brochures,...) https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT2517-1BF40

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT2517-1BF40

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RT2517-1BF40


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)


=3RT2517-1BF40&lang=en http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=


Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RT2517-1BF40/char

Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT2517-1BF40&objecttype=14&gridview=view1







last modified:

12/1/2021 🖸

7/5/2022