

## **Micro-RTU USB**



- Full Electric Power Industry Compliance
- Compact Design for Poletop or Substation Applications
- Multiple Protocols for SCADA Master
- Historical Data for all I/O Points
- TCP/IP (Ethernet) Interface
- Also Available in a Plastic Enclosure
- Custom Applications our Specialty

## **Specifications:**

- Control Sequence: Direct or SBO
- 4 Relay Contacts: Form C, 2 Amps at 30Vdc (resistive load)
- 8 Status Inputs
- Status Input Voltage: 12Vdc to 35Vdc, positive or negative polarity
- Input Current: 0.1ma (typical)
- Isolation: Optical
- Phase-to-Ground 2000V
- Input Voltage: 12Vdc to 35Vdc
- Communication Links: 1 USB Port, 1 TCP/IP RJ-45 Port
- Available with DNP 3.0, Modbus, PG&E (Data 2179), or Telegyr 8979
- Dimensions: 5.7" x 7"

The Micro-RTUs come with a free copy of the VisiCal software suite that allows it to be configured, calibrated, scanned, monitored or programmed with drag-and-drop and pushbutton simplicity.

🚬 Thionery RTU Calibration - Nicro RTU / Controller 💦 🔽 🔣		🚬 Tisionary RTU Calibration - Micro RTU / Controller 💿 🖬 🖬	
Die Belo		Die Deb	
Name Name Name   By South Statustics   Statustics South Status	Det 2 2 Publicit: 40 Blanch; 102 103 100.       To Construct of the Blanch; 102 100.       To Construct of the Blanch; 102 100.       To Construct of the Blanch; 102 100.       Construct of the Blanch; 102 100. <th col<="" th=""><th>0:00     Same Strate Strategies       Same Strate Strategies     Same Strategies       Same Strate Strategies     Same Strategies       Same Strate Strategies     Same Strategies       Same Strate Strate     Same Strategies       Same Strate Strate     Same Strate Strate       Same Strate     Same Strate</th></th>	<th>0:00     Same Strate Strategies       Same Strate Strategies     Same Strategies       Same Strate Strategies     Same Strategies       Same Strate Strategies     Same Strategies       Same Strate Strate     Same Strategies       Same Strate Strate     Same Strate Strate       Same Strate     Same Strate</th>	0:00     Same Strate Strategies       Same Strate Strategies     Same Strategies       Same Strate Strategies     Same Strategies       Same Strate Strategies     Same Strategies       Same Strate Strate     Same Strategies       Same Strate Strate     Same Strate Strate       Same Strate     Same Strate
Centinued Scan. Or	Analog AL D Analog D Analog D D	Evap the point vent to the      A prod/21() -Maximum Demand S + Mass Custer Mass Put New, and 4. prod/21() -Maximum Demand Ground Custer 15. (Pol/208) - Maximum Demand Ground Custer	